



Hochschule
München (HM)
University of
Applied Sciences

Laboratory for
Mechatronic
and Renewable
Energy Systems
(LMRES)

T3 – Advanced optimal feedforward torque control and operation management of electrical drives

Christoph M. Hackl

(with M. Buettner, H. Eldeeb, L. Horlbeck, J. Kullick, N. Monzen, A. Thommessen and J. Rossmann)

christoph.hackl@hm.edu

19.06.2023 – ISIE 2023, Aalto University, Helsinki



Outline

- 1 Introduction
- 2 Advanced optimal feedforward torque control (OFTC) and operation management of electrical drives
- 3 Conclusion

Outline

1 Introduction

- Research environment
- Research projects and expertise
- Selected research results

Outline

1 Introduction

- Research environment
- Research projects and expertise
- Selected research results

Introduction

Research environment: HM (www.hm.edu), ISES (ises.hm.edu) and LMRES (lmres.ee.hm.edu)



HM – Munich University of Applied Sciences

- 14 departments
- >18.000 students
- ~480 professors
- 3 campuses

ISES – Institute for Sustainable Energy Systems

- 6 research labs (6 professors)
- 27 PhD candidates

LMRES – Laboratory for Mechatronics and Renewable Energy Systems

- International team
- 13 PhD candidates (status 2023)
- >150 publications / >5.4 Mio. € raised




Outline

1 Introduction

- Research environment
- Research projects and expertise
- Selected research results

Introduction

LMRES – Research projects and research goals




Introduction


LMRES – Interdisciplinary expertise & publications



System identification
[9–26]



Friction
[27–29]



Non-identifier based adaptive control [14, 27, 30–46]



Paper coating machines
[4–8]



Supervision & teaching (Award)
[157–163]



Mechatronics & robotics
[27, 28, 40, 46–58]



Electro-active polymers
[1–3]

Mechatronic and renewable energy systems



Power electronics
[19–21, 46, 58–88]



Wind energy, renewables & smart grid [13–15, 44, 46, 57, 58, 60, 61, 67, 68, 70–72, 74, 79, 87, 93–95, 98, 100, 107, 112, 120, 132, 136, 139–156]



Electrical machines & drives [13, 15, 17, 23–27, 30, 32, 33, 45, 46, 51, 55, 57, 69, 77, 78, 80, 89–138]

Outline

1 Introduction

- Research environment
- Research projects and expertise
- Selected research results

Introduction

LMRES – Selected research results: Electrical/industrial/traction drives (reliability) [115]

6746

IEEE TRANSACTIONS ON INDUSTRIAL ELECTRONICS, VOL. 66, NO. 9, SEPTEMBER 2019



Postfault Full Torque–Speed Exploitation of Dual Three-Phase IPMSM Drives

Hisham M. Eldeeb , Ayman S. Abdel-Khalik , Senior Member, IEEE, and Christoph Michael Hackl , Senior Member, IEEE

Abstract—This paper exploits the torque–speed operating limits of a dual three-phase interior permanent magnet synchronous machine (ADT-IPMSM) during postfault operation for different neutral configurations. To achieve the maximum permissible torque–speed limits, the study proposes software and hardware modifications to the latest fault-tolerant techniques using: an offline optimization that takes into account simultaneously the voltage and current constraints during postfault operation and a simple hardware addition that modifies the neutral points configuration to either isolated (1N) or connected (2N) based on the operating torque and/or speed. Compared to the literature, the proposed study considers the field-weakening operation, extending the permissible achievable speeds. A 2.5-kW ADT-IPMSM prototype validates the theoretical findings.

Index Terms—Dual three phase, fault-tolerance, interior permanent magnet synchronous machine (IPMSM), post-fault control.

NOMENCLATURE

Notation
 $\mathbb{R}, \mathbb{N}$ Set of real and natural numbers.
 $n, m \in \mathbb{N}$ Number of rows and columns.
 $\zeta \in \mathbb{R}$ Real scalar.
 $\zeta \in \mathbb{R}^n$ Real vector (bold), expressed as $\zeta = (\zeta_1, \zeta_2, \dots, \zeta_n)^T$.
 $\|\zeta\|$ Euclidean norm of ζ .
 $\|\zeta\|_1$ The maximum sum of ζ_i is $\|\zeta\|_1$.

Subscripts and superscripts

$\top$ Transpose operator applied to vector or matrix.
 $\square_s$ Phasor description of a variable at *steady state*.
 $\square_\lambda$ Subscript “s” denotes referencing to the stator.
 $\square_\Lambda$ Superscripts “ Λ ” and “ λ ” are arbitrary variables representing the coordinates of a subspace ($\Lambda \in \{dq, XY, 0^+0^-, \lambda \in \{dq, XY, 0^+0^-\}$, and $\Lambda \neq \lambda$).

General

$T_{VSD} \in \mathbb{R}^{6 \times 6}$ Vector space decomposition matrix.
 $T_1(\phi) \in \mathbb{R}^{2 \times 2}$ Park’s transformation with angle $\phi \in \mathbb{R}$.
 $T_k \in \mathbb{R}^{3 \times 2}$ Optimization matrix.
 k_1^p, k_2^p Scalar optimization parameters in T_k of the $\Gamma \in \{X, Y\}$ coordinate.
 $J \in \mathbb{R}^{2 \times 2}$ Rotation matrix.
 u Electrical voltage (V).
 i Electrical current (A).
 ψ Flux linkage (Wb).
 $\zeta_{a_1 \dots a_n} \in \mathbb{R}^6$ Stator space vector expressed in the $(a_1 b_1 c_1 - a_2 b_2 c_2)$ frame, where $\zeta \in \{u, \psi, i\}$.
 u_{dc} DC-link voltage (V).
 m_e Electromechanical torque (N-m).
 $m_{e,max}$ Maximum torque for a given neutral point configuration (N-m).
 m_{load} Load torque (N-m).
 λ Arbitrary variable.




Fig. 1. Postfault comparison of the permissible (m_e, ω_e) characteristics between the presented algorithm in [7] and proposed optimum C with respect to the (a) 1N and (b) 2N neutral configurations, showing the enhancement in terms of extending the permissible




Fig. 2. Postfault efficiency maps of (a) 1N and (b) 2N connections within the (m_e, ω_e) range of the proposed optimization in Section III-C

Introduction

LMRES – Selected research results: Wind energy systems & power electronics (reliability; VDE Award) [78]

Modeling and Control of Permanent-Magnet Synchronous Generators Under Open-Switch Converter Faults

Christoph M. Hackl , Senior Member, IEEE, Urs Pecha , and Korbinian Schechner 

Abstract—The mathematical modeling of open-switch faults in two-level machine-side converters and the fault-tolerant current control of isotropic permanent-magnet synchronous generators are discussed in this paper. The proposed converter model is generic for any open-switch fault and independent of the operation mode of the electrical machine. The proposed fault-tolerant current control system gives improved control performance and reduced torque ripple under open-switch faults by modifying the antiwindup strategy, adapting the space-vector modulation scheme, and by injecting additional reference currents. The theoretical derivations of model and control are validated by comparative simulation and measurement results.

Index Terms—Antiwindup (AW), current control, d -current injection, fault tolerance, field-oriented control (FOC), flat-top modulation, open-switch fault, permanent-magnet synchronous generator (PMSG), wind turbine systems.

Notation: $\mathbb{N}, \mathbb{R}$: natural and real numbers. $x := (x_1, \dots, x_n)^T \in \mathbb{R}^n$: column vector, $n \in \mathbb{N}$ where $n^T :=$ and “ $\top$ ” mean “transposed” and “is defined as.” $I_n := \text{diag}(1, \dots, 1) \in \mathbb{R}^{n \times n}$: identity matrix. $O_{n \times p} \in \mathbb{R}^{n \times p}$: zero matrix, $n, p \in \mathbb{N}$. $x \in \mathbb{R}^n$ (in X): physical quantity x where each of the n elements has SI unit X . $\text{mod}(x, y)$: remainder of the division x/y , $x \in \mathbb{R}$, $y \in \mathbb{R} \setminus \{0\}$. $\text{atan2}: \mathbb{R}^2 \rightarrow [-\pi, \pi)$, $(x, y) \rightarrow \text{atan2}(y, x)$: extension of the inverse tangent function to whole circle. $T_{\frac{\pi}{2}} := \frac{1}{\sqrt{2}} \begin{bmatrix} 1 & -j \\ j & 1 \end{bmatrix}$ and $T^{-1} :=$


$T_p(\phi) := \begin{bmatrix} \cos(\phi) & -\sin(\phi) \\ \sin(\phi) & \cos(\phi) \end{bmatrix} =: T_p(-\phi)^{-1}$: Park transformation matrix. $J = \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix}$: rotation matrix.

I. INTRODUCTION

OPEN-SWITCH faults in converters for electric drives have gained increasing attention in the last years. An open-switch fault can be caused by thermic cycling, driver failures, or by a rupture of the insulated-gate bipolar transistor (IGBT) that is induced by a short-circuit fault [1]. Unlike a short-circuit fault, an open-switch fault does usually not trigger a system shutdown, but degrades the system performance and can cause—without proper counteractions—secondary faults in other components (see [2] and [3]). Open-switch faults are therefore a crucial kind of faults in converters and should be considered in the design of a robust and fault-tolerant (hence more reliable) electrical drive system.

This far, especially, the detection of faults in the converter and the identification of the faulty switch have been the focus of research. Various detection methods have already been presented [1]–[9]. Therefore, fault detection is *not* the topic of this paper.

The focus of this paper is on a fault-tolerant modification of the control system such that, even in the presence of an open-switch fault in the machine-side converter, a continuous



13. Comparison of simulation and measurement results for standard control system and fault-tolerant control system with extended AW, modifi u (flat-top modulation), and optimally injected d -current. (a) Experiment (E_1): Comparison of simulation and measurement results for standard control; $\text{THD}_{id} = 41.8\%$ (simulation) versus $\text{THD}_{id,\max} = 45.4\%$ (measurement). (b) Experiment (E_2): Comparison of simulation and measurement results for fault-tolerant control system with extended AW, modifi u (flat-top modulation), and optimally injected d -current; $\text{THD}_{id} = 41.8\%$ (simulation) versus $\text{THD}_{id,\max} = 45.4\%$ (measurement).

Introduction

LMRES – Selected research results: Traction drives & power electronics (efficiency; Cooperation with BMW) [128]

3760

IEEE TRANSACTIONS ON INDUSTRIAL ELECTRONICS, VOL. 68, NO. 5, MAY 2021



Synchronous Optimal Pulsewidth Modulation for Synchronous Machines With Highly Operating Point Dependent Magnetic Anisotropy

Athina Birda , Joerg Reuss , and Christoph M. Hackl , Senior Member, IEEE

Abstract—The performance of synchronous optimal pulsewidth modulation is investigated for the control of an automotive low voltage electrical drive system, which consists of a two-level voltage source inverter and an interior permanent magnet synchronous motor. The machine magnetic anisotropy varies due to magnetic saturation and cross-saturation effects and depends on the motor operating point. The main objective of this article is to investigate the influence of the varying magnetic anisotropy on the optimized half-wave symmetric inverter pulse patterns. For this purpose, the optimized inverter switching angles are derived by minimizing the current harmonic distortion of an isotropic and anisotropic permanent magnet synchronous motor. Their performance is evaluated and compared by experimental results.

Index Terms—Electric vehicle, magnetic anisotropy, permanent magnet synchronous motor (PMSM), synchronous optimal pulsewidth modulation (SOPWM).

I. INTRODUCTION

AS PART of the global effort to reduce the CO₂ emissions, the interest of the automotive industry over the last years focused on the concept of electric mobility. Still, the limited operating range and increased price of electric vehicles remain the most important obstacles for their wide spread. The efficiency of the electrical drive system and, by that, the operating range of electric vehicles can be improved by optimizing the inverter

compromising the motor current quality. To this end, the optimized inverter pulse patterns are determined, which minimize the harmonic distortion of the phase currents. The optimization procedure is conducted offline and the resulting optimized switching angles are stored in lookup tables (LUTs). Since the switching frequency f_{sw} is synchronized with the fundamental stator frequency f_r , the pulse number

$$q := f_{sw} / f_r \quad (1)$$

is always an integer [1].

SOPWM is primarily employed in medium voltage high power induction motor drive applications, where the reduction of switching losses is of utmost importance [1], [2]. Moreover, it is a common modulation strategy for operating electric rail traction converters adopted by GE [3] and SIEMENS [4]. On the contrary, little research has been conducted when the SOPWM strategy is employed for the control of synchronous motor drives [5]–[13]. Especially, SOPWM has not yet been explored for automotive low-voltage interior permanent magnet synchronous motor (IPMSM) drives with highly operating point (OP) dependent magnetic anisotropy. This is the main motivation of this article.

In [5]–[7], the current harmonic content of an isotropic permanent magnet synchronous motor (PMSM) drive is min-




Fig. 9. Numerical performance evaluation of the optimization results. (a) $I_{s,THD}(\alpha_{aniso})/\%$. (b) $I_{s,THD,dev}/\%$.

Nonlinear Modeling, Identification, and Optimal Feedforward Torque Control of Induction Machines Using Steady-State Machine Maps

Julian Kullick and Christoph M. Hackl, Senior Member, IEEE


Abstract—A novel but simple machine map-based modeling, identification, and optimal feedforward torque control (OFTC) approach for induction machines (IMs) is presented. It is based on, first, a generic, nonlinear transformer-like machine model considering nonlinear flux linkages (with magnetic saturation and cross coupling) and iron losses in the stator laminations in a novel, arbitrarily rotating but unique, robust, and reproducible (d, q) -reference frame; second, a holistic machine identification procedure, which evaluates steady-state measurements over a grid of (d, q) stator currents and produces temperature and frequency dependent machine maps, for example, flux linkages, torque, iron resistance, and efficiency; and third, a numerical offline optimization and extraction of different OFTC look-up tables (LUTs) for optimal current reference generation depending on reference torque and electrical frequency (and temperature). During the identification, stator winding temperature and electrical stator frequency of the IM are kept constant by an intelligent temperature and the speed control system. The presented measurement results for a squirrel-cage IM confirm that compared to constant flux operation or scalar V/Hz control, efficiency can be increased particularly in part-load operation by up to 7% by Maximum Efficiency Per Losses minimizing copper and iron losses.

Index Terms—Efficiency, flux linkages, induction machine (IM), iron resistance, machine identification, MTPA.

$\|x\| := \sqrt{x^T x} = \sqrt{x_1^2 + \dots + x_n^2}$: Euclidean norm of x ; $X \in \mathbb{R}^{n \times n}$: matrix (n rows & columns); X^{-1} , X^{-T} : inverse, inverse transpose of X (if exist), resp.; $I_n := \text{diag}(1, \dots, 1) \in \mathbb{R}^{n \times n}$: identity matrix; $0_n := (0, \dots, 0)^T \in \mathbb{R}^n$: zero vector; $x^{dq} := (x^d, x^q)^T \in \mathbb{R}^2$: stator or rotor (iron) current, voltage, flux linkage vectors, i.e., $x \in \{i_{s/r}^{dq}, u_{s/r}^{dq}, \psi_{s/r}^{dq}, \delta\}$; $X^{dq} := \begin{bmatrix} X^d & X^q \\ X^{qd} & X^q \end{bmatrix} \in \mathbb{R}^{2 \times 2}$: stator/rotor (iron) resistance matrix, i.e., $R_{s/r}^{dq}$; $\vartheta_{s/r}$: stator/rotor temperature; x_{ref} : reference value of, e.g., temperature, electrical frequency, and currents, i.e., $x \in \{\vartheta_{s,ref}, \omega_{p,ref}, i_{s,ref}^d, i_{s,ref}^q, \delta\}$; $T_{s/r}$: rotor/filter time constant; n_p : pole pair number; m_m : machine/load torque; Θ_m : machine inertia; ω_m : mechanical angular velocity; ϕ_p and $\omega_p = \frac{d}{dt}\phi_p$: Park transformation angle and angular velocity; $J := \begin{bmatrix} 0 & -1 \\ 1 & 0 \end{bmatrix}$: rotation matrix (by $\frac{\pi}{2}$).

I. MOTIVATION AND CONTRIBUTIONS

Maximum efficiency operation (or loss minimizing control) of induction machines has been subject to extensive research in



12. Efficiency comparison for $\omega_p \in [0.2, 0.6, 1] \cdot \omega_{p,N}$ (from top to bottom), with efficiency contour plots in current locus (left column), efficiency-over-torque plots (middle column) and overall performance bar plots (right column).

Introduction

LMRES – Selected research results: Electrical/industrial/traction drives (self-commissioning) [25]



Received 26 February 2022; revised 17 March 2022; accepted 22 March 2022. Date of publication 25 March 2022; date of current version 12 May 2022. The review of this paper was arranged by Associate Editor Halilhan Abu-Rub.

Digital Object Identifier 10.1109/JIE.2022.3162595

Analytical Prototype Functions for Flux Linkage Approximation in Synchronous Machines


SHIH-WEI SU¹, CHRISTOPH M. HACKL² (Senior Member, IEEE),
AND RALPH KENNEL¹ (Senior Member, IEEE)

¹ Institute of Electrical Drive System and Power Electronics, Technical University of Munich, 80333 Munich, Germany


² Department of Electrical Engineering and Information Technology, Hochschule München University of Applied Sciences, 80335 Munich, Germany

CORRESPONDING AUTHOR: SHIH-WEI SU (e-mail: shihwei.su@tum.de).


ABSTRACT Physically motivated and analytical prototype functions are proposed to approximate the nonlinear flux linkages of nonlinear synchronous machines (SMs) in general; and reluctance synchronous machines (RSMs) and interior permanent magnet synchronous machines (IPMSMs) in particular. Such analytical functions obviate the need of huge lookup tables (LUTs) and are beneficial for optimal operation management and nonlinear control of such machines. The proposed flux linkage prototype functions are capable of mimicking the nonlinear self-axis and cross-coupling saturation effects of SMs. Moreover, the differentiable prototype functions allow to easily derive analytical expressions for the differential inductances by simple differentiation of the analytical flux linkage prototype functions. In total, two types of flux linkage prototype functions are developed. The first flux linkage approximation is rather simple and obeys the energy conservation rule for “symmetric” flux linkages of RSMs. With the gained knowledge, the second type of prototype functions is derived in order to achieve approximation flexibility necessary for SMs with permanent (or electrical) excitation with “unsymmetric” flux linkages due to the excitation offset. All proposed flux




(a)



(a)



(b)



(b)

TT 04-2 Electrical Machines and Drives (Y405)

Monday, 19 June 2023 @ 17:20-17:40 (ISIE23-000129)

B. Pfeifer et al, “A simple disturbance observer for stator flux linkage estimation of nonlinear synchronous machines”

Introduction

LMRES – Selected research results: Smart grid/renewables/power systems (grid synchronisation) [22]

Modified Second-Order Generalized Integrators With Modified Frequency Locked Loop for Fast Harmonics Estimation of Distorted Single-Phase Signals

Christoph M. Hackl[✉], Senior Member, IEEE, and Markus Landerer

Abstract—This article proposes *modified second-order generalized integrators* (mSOGIs) for a fast estimation of all harmonic components of arbitrarily distorted single-phase signals, such as voltages or currents in power systems. The estimation is based on the internal model principle leading to an overall observer consisting of parallelized mSOGIs. The observer is tuned by pole placement. For a constant fundamental frequency, the observer is capable of estimating all harmonic components with prescribed settling time by choosing the harmonic poles appropriately. For time-varying fundamental frequencies, the harmonic estimation is combined with a *modified frequency locked loop* (mFLL) with gain normalization, sign-correct antipwindup, and rate limitation. The estimation performances of the proposed parallelized mSOGIs with and without mFLL are illustrated and validated by measurement results. The results are compared to standard approaches such as parallelized standard SOGIs (sSOGIs) and adaptive notch filters (ANFs).

Index Terms—Amplitude estimation, frequency estimation, frequency-locked loop (FLL), phase estimation, second-order generalized integrator (SOGI).

Notation

$\mathbb{N}, \mathbb{R}, \mathbb{C}, \mathbb{Q}$: natural, real, complex and rational numbers. For the following, let $n, m \in \mathbb{N}$. $\mathbf{x} := (x_1, \dots, x_n)^T \in \mathbb{R}^n$: column vector (where $\cdot :=$ means “is defined as” and T means “transposed”); $\mathbf{0}_n := (0, 0, \dots, 0)^T \in \mathbb{R}^n$: zero vector; $\|\mathbf{x}\| := \sqrt{\mathbf{x}^T \mathbf{x}}$: Euclidean norm of $\mathbf{x}$. $\mathbf{A} \in \mathbb{R}^{n \times m}$: real (non-square) matrix; $\text{diag}(\mathbf{a}) \in \mathbb{R}^{n \times n}$: diagonal matrix with

IEEE TRANSACTIONS ON POWER ELECTRONICS, VOL. 35, NO. 3, MARCH 2020

I. INTRODUCTION

A. Motivation and Literature Review

IN VIEW of the increasing number of decentralized generation units with power electronics-based grid connection and the decreasing number of large-scale generators, the overall inertia in the grid is diminishing. This results in faster and more abrupt frequency fluctuations and significant harmonic distortion of physical quantities (such as currents or voltages) of the power system [1]. Fast frequency fluctuations endanger stability of the power grid. Significant harmonic distortions of voltages and currents can degrade power quality and lead to damage or even destruction of grid components. To be capable of taking appropriate countermeasures such as 1) improving system stability and power quality and 2) compensating for such deteriorated operation conditions, it is crucial to detect and estimate fundamental and higher harmonic components of the considered quantities in real time as fast and accurate as possible. Modern power electronic devices (e.g., flexible ac transmission systems or grid-connected converters of decentralized renewable energy systems) can then be used to implement such countermeasures. That is why, grid state estimation became of particular interest to the research community in the past years and has been studied extensively (see e.g., [2]–[24] to name a few).

It is well known that a signal with significant harmonic




Fig. 11. Measurement results for Scenario (S4): Comparison of the estimation performances of parallelized mSOGIs (—), sSOGIs (---), and ANFs (— · —) without FLL. Signals shown from top to bottom are: Harmonic signals y_1 to y_{10} (— · —) and their estimates $\hat{y}_1$ to $\hat{y}_{10}$ and harmonic estimation errors $e_1 = y_1 - \hat{y}_1$ to $e_{10} = y_{10} - \tilde{y}_{10}$.

frequency are identical for this scenario. Therefore, the estimation performances purely can be compared according to the respective observer tunings only. The fundamental signal $y = y_1$ undergoes step-like changes in amplitude, phase and amplitude and phase as described above.

The estimation performances of fundamental mSOGI (—), fundamental sSOGI (---), and fundamental ANF (— · —) are shown in Fig. 7. The first and second subplots show input signal $y = y_1$ (— · —) and its estimates $\hat{y} = \hat{y}_1$ and the estimation errors $e_y = y_1 - \hat{y}_1$, respectively. All three observers are capable of estimating the input signal y . All estimation errors $e_u \rightarrow 0$ tend to

2 Advanced optimal feedforward torque control (OFTC) and operation management of electrical drives

- Motivation
- Problem statement and proposed solution
- OFTC with analytical ORCC
 - Analytical computation
 - Operation strategies
 - Operation management and decision tree
 - Implementation results
- OFTC with ANN-based ORCC
 - Overview
 - Artificial Neural Network Design
 - Implementation results

2 Advanced optimal feedforward torque control (OFTC) and operation management of electrical drives

- Motivation
- Problem statement and proposed solution
- OFTC with analytical ORCC
 - Analytical computation
 - Operation strategies
 - Operation management and decision tree
 - Implementation results
- OFTC with ANN-based ORCC
 - Overview
 - Artificial Neural Network Design
 - Implementation results

Motivation

Electrical machines: Widely-used, compact and efficient actuators



www.miele.de



www.farmwood.co.uk



www.abb.com (from video)



www.siemens.com



TT 05-2 Power Electronics & Energy Conversion (C Hall)

Monday, 19 June 2023 @ 11:00-11:20 (ISIE23-000045)

L. Testa et al, "A generic Lyapunov-based Observer for Double-Star-Chopper-Cell/Bridge-Cell Modular-Multilevel-Cascade-Converters"


TT 05-5 Power Electronics (C Hall)

Tuesday, 20 June 2023 @ 09:00-09:20 (ISIE23-000108)

O. Kalmbach et al, "I/O-Linearization Based Current Decoupling Control of Modular Multilevel Cascade Converters"

Motivation


Examples of anisotropic synchronous machines [164] with “saliency ratio” $L_s^d/L_s^q \neq 1$



$$m_m(i_s^d, i_s^q) = \frac{2n_p}{3\kappa^2} (i_s^{dq})^\top \mathbf{J} \psi_s^{dq} \stackrel{\text{(const. Para.)}}{=} \frac{2n_p}{3\kappa^2} \left[\underbrace{\tilde{\psi}_{pm} i_s^q}_{\text{magnetic torque}} + \underbrace{(\tilde{L}_s^d - \tilde{L}_s^q) i_s^d i_s^q}_{\text{reluctance torque}} + \underbrace{\tilde{L}_{s,m} ((i_s^q)^2 - (i_s^d)^2)}_{\text{cross-coupling torque}} \right]$$

Motivation


Optimal feedforward torque control problem: **Isotropic, linear PMSM** (without iron losses)



$$m_{m,\text{ref}} \stackrel{!}{=} m_m(i_s^d, i_s^q) = \frac{2n_p}{3\kappa^2} \psi_{\text{pm}} i_s^q \implies \mathbf{i}_{s,\text{ref}}^{dq} := (i_{s,\text{ref}}^d, i_{s,\text{ref}}^q)^\top = \left(0, \frac{3\kappa^2 m_{m,\text{ref}}}{2n_p \psi_{\text{pm}}}\right)^\top$$

Motivation

Optimal feedforward torque control problem: **Anisotropic, affine PMSM** (without iron losses)




$$m_{m,\text{ref}} \stackrel{!}{=} m_m(i_s^{dq}) = \frac{2n_p}{3\kappa^2} \left[\tilde{\psi}_{\text{pm}} i_s^q + (\tilde{L}_s^d - \tilde{L}_s^q) i_s^d i_s^q + \tilde{L}_{s,m} ((i_s^q)^2 - (i_s^d)^2) \right] \implies \boxed{i_{s,\text{ref}}^{dq} := (\text{?}, \text{?})^\top}$$


Motivation

Optimal feedforward torque control problem: **Identical for all nonlinear machines**

Nonlinear IPMSM (3.9 kW@5 500 rpm)



Nonlinear IM (3 kW@1 445 rpm)



TT 04-2 Electrical Machines and Drives (Y405)

Monday, 19 June 2023 @ 16:20-16:40 (ISIE23-000071)

J. Rossmann et al, "Nonlinear Three-Phase Reluctance Synchronous Machine Modeling With Extended Torque Equation"

TT 03-2 Power Systems and the Smart Grid, Renewable Energy Systems and Smart Grid (D Hall)

Monday, 19 June 2023 @ 16:40-17:00 (ISIE23-000035)


A. Thommessen et al, "Combining virtual synchronous machine and feedforward torque control for doubly-fed induction machine based wind energy conversion systems"

2 Advanced optimal feedforward torque control (OFTC) and operation management of electrical drives

- Motivation
- Problem statement and proposed solution
- OFTC with analytical ORCC
 - Analytical computation
 - Operation strategies
 - Operation management and decision tree
 - Implementation results
- OFTC with ANN-based ORCC
 - Overview
 - Artificial Neural Network Design
 - Implementation results


Problem statement and proposed solution

Optimal feedforward torque control (OFTC) within the control system



Problem statement and proposed solution

Optimal feedforward torque control (OFTC) problem: Optimal reference current computation (ORCC)



$$\mathbf{i}_{s,ref}^{dq}(m_{m,ref}, \hat{u}_{s,max}, \hat{i}_{s,max}, \omega_p, \dots) = \begin{pmatrix} i_{s,ref}^d(m_{m,ref}, \hat{u}_{s,max}, \hat{i}_{s,max}, \omega_p, \dots) \\ i_{s,ref}^q(m_{m,ref}, \hat{u}_{s,max}, \hat{i}_{s,max}, \omega_p, \dots) \end{pmatrix}$$


✓ Numerical solutions and/or look-up tables
(but: limited storage, accuracy, real-time applicability)

? Analytical solutions

(some do exist but impose simplifying assumptions such as $R_s = 0$, $R_{s,Fe} = 0$ and/or $L_{s,m} = 0$, etc.)

Problem statement and proposed solution

Considered anisotropic synchronous machines with iron losses: **Nonlinear transformer model**



with $\psi_s^{dq} = \psi_{s,Fe}^{dq}$ (single assumption!) and (possibly) *nonlinear*

- *current, angle, speed and temperature dependent stator resistance, i.e.* $R_s^{dq} := R_s^{dq}(i_s^{dq}, \phi_p, \omega_p, \vartheta_s)$
- *current, angle, speed and temperature dependent iron resistance, i.e.* $R_{s,Fe}^{dq} := R_{s,Fe}^{dq}(i_s^{dq}, \phi_p, \omega_p, \vartheta_s)$
- *current, angle, speed and temperature dependent flux linkages, i.e.* $\psi_s^{dq} := \psi_s^{dq}(i_s^{dq}, \phi_p, \omega_p, \vartheta_s)$


Problem statement and proposed solution

Considered anisotropic synchronous machines with iron losses: **Nonlinear machine dynamics** ($\implies$ steady-state model)

$$\begin{aligned}
 \text{Stator:} \quad & \underbrace{\begin{pmatrix} u_s^d \\ u_s^q \end{pmatrix}}_{=: \mathbf{u}_s^{dq}} = \underbrace{\begin{bmatrix} R_s^d & R_s^{dq} \\ R_s^{qd} & R_s^q \end{bmatrix}}_{=: \mathbf{R}_s^{dq}} \underbrace{\begin{pmatrix} i_s^d \\ i_s^q \end{pmatrix}}_{=: \mathbf{i}_s^{dq}} + \omega_p \underbrace{\begin{bmatrix} 0 & -1 \\ 1 & 0 \end{bmatrix}}_{=: \mathbf{J}} \underbrace{\begin{pmatrix} \psi_s^d \\ \psi_s^q \end{pmatrix}}_{=: \mathbf{\psi}_s^{dq}} + \cancel{\frac{d}{dt} \psi_s^{dq}} \\
 \text{Iron:} \quad & \underbrace{\begin{pmatrix} 0 \\ 0 \end{pmatrix}}_{=: \mathbf{0}_2} = \underbrace{\begin{bmatrix} R_{s,Fe}^d & R_{s,Fe}^{dq} \\ R_{s,Fe}^{qd} & R_{s,Fe}^q \end{bmatrix}}_{=: \mathbf{R}_{s,Fe}^{dq}} \underbrace{\begin{pmatrix} i_{s,Fe}^d \\ i_{s,Fe}^q \end{pmatrix}}_{=: \mathbf{i}_{s,Fe}^{dq}} + \omega_p \mathbf{J} \mathbf{\psi}_s^{dq} + \cancel{\frac{d}{dt} \psi_s^{dq}} \\
 & \mathbf{i}_{s,Fe}^{dq} = -(\mathbf{R}_{s,Fe}^{dq})^{-1} \left[\omega_p \mathbf{J} \mathbf{\psi}_s^{dq} + \cancel{\frac{d}{dt} \psi_s^{dq}} \right] \\
 \text{Mech.:} \quad & \frac{d}{dt} \omega_m = \frac{1}{\Theta_m} (m_m + m_l) \quad \text{with} \quad \omega_p = n_p \omega_m \\
 & m_m = \frac{2}{3\kappa^2} (\mathbf{i}_s^{dq} + \mathbf{i}_{s,Fe}^{dq})^\top \mathbf{J} \mathbf{\psi}_s^{dq} \\
 \text{Losses:} \quad & p_{s,L} = \underbrace{\frac{2}{3\kappa^2} (\mathbf{i}_s^{dq})^\top \mathbf{R}_s^{dq} \mathbf{i}_s^{dq}}_{=: p_{s,Cu}} + \underbrace{\frac{2}{3\kappa^2} (\mathbf{i}_{s,Fe}^{dq})^\top \mathbf{R}_{s,Fe}^{dq} \mathbf{i}_{s,Fe}^{dq}}_{=: p_{s,Fe}}
 \end{aligned}$$

Problem statement and proposed solution

Optimal reference current computation (ORCC): Optimization problem(s) with multiple constraints



$$\max_{\mathbf{i}_s^{dq} \in \mathbb{F}} -f(\mathbf{i}_s^{dq}) \quad \text{subject to}$$

$$\left\{ \begin{array}{l} \|\mathbf{i}_s^{dq}\|^2 \leq \hat{i}_{s,\max}^2, \\ \text{(current circular area)} \\ \|\mathbf{u}_s^{dq}(\mathbf{i}_s^{dq}, \omega_p, \dots)\|^2 \leq \hat{u}_{s,\max}^2, \\ \text{(voltage elliptical area)} \\ |m_m(\mathbf{i}_s^{dq}, \omega_p, \dots)| \leq |m_{m,\text{ref}}|, \\ \text{and } \text{sign}(m_{m,\text{ref}}) = \\ \text{sign}(m_m(\mathbf{i}_s^{dq})). \end{array} \right.$$

$\Rightarrow$ e.g. minimize copper losses,
i.e., $-f(\mathbf{i}_s^{dq}) = -\|\mathbf{i}_s^{dq}\|^2$.

$\Rightarrow \mathbf{i}_{s,\text{ref}}^{dq} = \mathbf{i}_{s,\text{MTPC}}^{dq}$ at ★, i.e., MTPC
with $m_{m,\text{ref}} = m_m(\mathbf{i}_{s,\text{ref}}^{dq})$ feasible.

Outline

2 Advanced optimal feedforward torque control (OFTC) and operation management of electrical drives


- Motivation
- Problem statement and proposed solution
- **OFTC with analytical ORCC**
 - Analytical computation
 - Operation strategies
 - Operation management and decision tree
 - Implementation results
- OFTC with ANN-based ORCC
 - Overview
 - Artificial Neural Network Design
 - Implementation results

OFTC with analytical ORCC: Analytical computation

Sequential Quadratic Programming (SCP): Linearization, implicit formulation, optimization & intersection points

Step 1: Online linearization of flux linkages, machine torque, iron resistance, etc.: for example:

- **flux linkages** (first-order Taylor approximation around operating point $\bar{i}_s^{dq}$ [■])
- **machine torque** (second-order Taylor approximation around operating point $\bar{i}_s^{dq}$ [■])



■ ...

OFTC with analytical ORCC: Analytical computation

Sequential Quadratic Programming (SCP): Linearization, implicit formulation, optimization & intersection points

Step 2: Derivation of quadrics $Q_A(\mathbf{i}_s^{dq}) := (\mathbf{i}_s^{dq})^\top \mathbf{A} \mathbf{i}_s^{dq} + 2\mathbf{a}^\top \mathbf{i}_s^{dq} + \alpha$:

- Current circular area: $(i_s^d)^2 + (i_s^q)^2 \leq \hat{i}_{s,\max}^2 \iff \|\mathbf{i}_s^{dq}\|^2 = (\mathbf{i}_s^{dq})^\top \mathbf{I}_2 \mathbf{i}_s^{dq} \leq \hat{i}_{s,\max}^2$

$$\implies \mathbb{I}(\hat{i}_{s,\max}) := \{ \mathbf{i}_s^{dq} \in \mathbb{R}^2 \mid (\mathbf{i}_s^{dq})^\top \mathbf{I}_2 \mathbf{i}_s^{dq} - \hat{i}_{s,\max}^2 \leq 0 \}$$

- (Linearized) Voltage elliptical area: $(u_s^d)^2 + (u_s^q)^2 \leq \hat{u}_{s,\max}^2 \iff \|\mathbf{u}_s^{dq}(\mathbf{i}_s^{dq}, \omega_p, \dots)\|^2 = \dots \leq \hat{u}_{s,\max}^2$

$$\implies \overline{\mathbb{V}}(\hat{u}_{s,\max}) := \{ \mathbf{i}_s^{dq} \in \mathbb{R}^2 \mid (\mathbf{i}_s^{dq})^\top \overline{\mathbf{V}}(\bar{\omega}_p) \mathbf{i}_s^{dq} + 2\bar{\mathbf{v}}(\bar{\omega}_p)^\top \mathbf{i}_s^{dq} + \bar{\nu}(\bar{\omega}_p, \hat{u}_{s,\max}) \leq 0 \}$$

- (Linearized) Reference torque hyperbola: $m_m(\mathbf{i}_s^{dq}, \omega_p, \dots) = \frac{3}{2}n_p(\mathbf{i}_s^{dq} + \mathbf{i}_{s,\text{Fe}}^{dq})^\top \mathbf{J}\boldsymbol{\psi}_s^{dq} \stackrel{!}{=} m_{m,\text{ref}} \iff \dots$

$$\implies \overline{\mathbb{T}}(m_{m,\text{ref}}) := \{ \mathbf{i}_s^{dq} \in \mathbb{R}^2 \mid (\mathbf{i}_s^{dq})^\top \overline{\mathbf{T}} \mathbf{i}_s^{dq} + 2\bar{\mathbf{t}}^\top \mathbf{i}_s^{dq} - m_{m,\text{ref}} = 0 \}$$

■ ...

OFTC with analytical ORCC: Analytical computation

Sequential Quadratic Programming (SQP): Linearization, implicit formulation, optimization & intersection points

Step 3: Optimization problem with equality constraint

$$\max_{\mathbf{i}_s^{dq}} - \left(\underbrace{(\mathbf{i}_s^{dq})^\top \mathbf{A} \mathbf{i}_s^{dq} + 2\mathbf{a}^\top \mathbf{i}_s^{dq} + \alpha}_{=: Q_A(\mathbf{i}_s^{dq})} \right) \text{ s.t. } \underbrace{(\mathbf{i}_s^{dq})^\top \mathbf{B} \mathbf{i}_s^{dq} + 2\mathbf{b}^\top \mathbf{i}_s^{dq} + \beta}_{=: Q_B(\mathbf{i}_s^{dq})} = 0$$

$\Rightarrow$ Hyperbolas for e.g. MTPC, MTPL or MTPV (with $R_s, R_{s,Fe} \neq 0$ & $L_{s,m} \neq 0$, etc.)

Step 4: Intersection of two quadrics (e.g. voltage ellipse and current circle)

$$\mathbf{i}_{s,\text{ref}}^{dq} := \arg \min_{\|\mathbf{i}_s^{dq}\|} \left\{ \mathbf{i}_s^{dq} \in \mathbb{R}^2 \mid Q_A(\mathbf{i}_s^{dq}) = 0 \wedge Q_B(\mathbf{i}_s^{dq}) = 0 \right\}$$

$\Rightarrow$ Optimal operation point ★ (reference current; iteration possibly necessary)



Both lead to subproblem of solving a fourth-order (quartic) polynomial

$$\chi(\lambda) := c_4 \lambda^4 + c_3 \lambda^3 + c_2 \lambda^2 + c_1 \lambda + c_0 \stackrel{!}{=} 0$$

$\Rightarrow$ Analytical solutions exist (e.g. Euler's solution, see [165])

OFTC with analytical ORCC: Operation strategies


Overview



- Maximum Torque per Losses (MTPL) [purple] (or Maximum Torque per Current (MTPC) [blue])
- Maximum Current (MC) [orange] and Maximum Current extended (MC_{ext}) [yellow]
- Maximum Torque per Voltage (MTPV) [light blue] (or Maximum Torque per Flux (MTPF))
- Field Weakening (FW) [light green]

OFTC with analytical ORCC: Operation strategies

Maximum Torque per Current (**MTPC** @ $0 \cdot \omega_{m,R}$): Reference torque **feasible**



Optimization problem

$$\begin{aligned} \max_{\mathbf{i}_s^{dq} \in \bar{\mathbb{F}}} -p_{s,Cu}(\mathbf{i}_s^{dq}) \quad \text{s.t.} \\ \underbrace{(\mathbf{i}_s^{dq})^\top \bar{\mathbf{T}} \mathbf{i}_s^{dq} + 2 \bar{\mathbf{t}}^\top \mathbf{i}_s^{dq}}_{\approx m_m(\mathbf{i}_s^{dq})} - m_{m,\text{ref}} = 0 \end{aligned}$$

Solution set


$$\begin{aligned} \overline{\text{MTPC}}(\bar{\mathbf{i}}_s^{dq}, \bar{\omega}_p, \dots) &:= \{ \mathbf{i}_s^{dq} \in \mathbb{R}^2 \mid \\ &(\mathbf{i}_s^{dq})^\top \bar{\mathbf{M}}_C \mathbf{i}_s^{dq} + 2 \bar{\mathbf{m}}_C^\top \mathbf{i}_s^{dq} = 0 \} \end{aligned}$$

Optimal reference currents (★)

$$\mathbf{i}_{s,\text{MTPC}}^{dq} = \overline{\text{MTPC}} \cap \bar{\mathbf{T}}(m_{m,\text{ref}})$$

OFTC with analytical ORCC: Operation strategies

Maximum Torque per Losses (**MTPL** @ $1 \cdot \omega_{m,R}$): Reference torque **feasible**



Optimization problem

$$\begin{aligned} \max_{\mathbf{i}_s^{dq} \in \bar{\mathbb{F}}} & -p_{s,Cu}(\mathbf{i}_s^{dq}) - p_{s,Fe}(\mathbf{i}_s^{dq}) \quad \text{s.t.} \\ & \underbrace{(\mathbf{i}_s^{dq})^\top \bar{\mathbf{T}} \mathbf{i}_s^{dq} + 2 \bar{\mathbf{t}}^\top \mathbf{i}_s^{dq}}_{\approx m_m(\mathbf{i}_s^{dq})} - m_{m,ref} = 0 \end{aligned}$$

Solution set


$$\begin{aligned} \overline{\text{MTPL}}(\bar{\mathbf{i}}_s^{dq}, \bar{\omega}_p, \dots) &:= \{ \mathbf{i}_s^{dq} \in \mathbb{R}^2 \mid \\ & (\mathbf{i}_s^{dq})^\top \bar{\mathbf{M}}_L \mathbf{i}_s^{dq} + 2 \bar{\mathbf{m}}_L^\top \mathbf{i}_s^{dq} + \bar{\mu}_L = 0 \} \end{aligned}$$

Optimal reference currents (★)

$$\mathbf{i}_{s,MTPL}^{dq} = \overline{\text{MTPL}} \cap \bar{\mathbf{T}}(m_{m,ref})$$

OFTC with analytical ORCC: Operation strategies

Maximum Current (**MC** @ $2 \cdot \omega_{m,R}$): Reference torque **not feasible**



Optimization problem

$$\max_{\mathbf{i}_s^{dq} \in \bar{\mathbb{F}}} |(m_m(\mathbf{i}_s^{dq}))| \quad \text{s.t.} \\ \text{sign}(m_m) = \text{sign}(m_{m,\text{ref}})$$

Feasible set


$$\overline{\text{MC}}(\bar{\mathbf{i}}_s^{dq}, \bar{\omega}_p, \dots, \hat{u}_{s,\text{max}}, \hat{i}_{s,\text{max}}) := \\ \bar{\mathbb{V}}(\hat{u}_{s,\text{max}}) \cap \partial \mathbb{I}(\hat{i}_{s,\text{max}})$$

Optimal current reference (★)

$$\mathbf{i}_{s,\text{MC}}^{dq} = \partial \bar{\mathbb{V}}(\hat{u}_{s,\text{max}}) \cap \partial \mathbb{I}(\hat{i}_{s,\text{max}})$$

OFTC with analytical ORCC: Operation strategies

Maximum Current extended ($\overline{MC}_{\text{ext}}$ @ $1 \cdot \omega_{m,R}$): Reference torque **feasible**



Optimization problem

$$\max_{i_s^{dq} \in \overline{F}} |(m_m(i_s^{dq}))| \quad \text{s.t.}$$

$$\text{sign}(m_m) = \text{sign}(m_{m,\text{ref}})$$

Solution set

$$\overline{MC}_{\text{ext}}(\bar{i}_s^{dq}, \bar{\omega}_p, \dots, \hat{u}_{s,\text{max}}, \hat{i}_{s,\text{max}}) := \overline{V}(\hat{u}_{s,\text{max}}) \cap \partial I(\hat{i}_{s,\text{max}})$$


Optimal current reference (★)

$$i_{s,\text{MC}_{\text{ext}}}^{dq} = \overline{T}(m_{m,\text{ref}}) \cap \partial I(\hat{i}_{s,\text{max}})$$

$$\text{with } i_{s,\text{MTPL}}^d < i_{s,\text{MC}_{\text{ext}}}^d$$

OFTC with analytical ORCC: Operation strategies

Field Weakening (**FW** @ $1.40 \cdot \omega_{m,R}$): Reference torque **feasible**



Optimization problem

$$\begin{aligned} \max_{\mathbf{i}_s^{dq} \in \bar{F}} & -p_{s,Cu}(\mathbf{i}_s^{dq}) - p_{s,Fe}(\mathbf{i}_s^{dq}) \quad \text{s.t.} \\ & \underbrace{(\mathbf{i}_s^{dq})^\top \mathbf{T} \mathbf{i}_s^{dq} + 2 \mathbf{t}^\top \mathbf{i}_s^{dq}}_{=m_m(\mathbf{i}_s^{dq})} - m_{m,ref} = 0 \end{aligned}$$

Feasible set


$$\bar{FW}(\bar{i}_s^{dq}, \bar{\omega}_p, \dots, m_{m,ref}, \hat{u}_{s,max}, \hat{i}_{s,max}) := \bar{F}(\hat{u}_{s,max}, \hat{i}_{s,max}) \cap \bar{T}(m_{m,ref})$$

Optimal reference currents (★)

$$\mathbf{i}_{s,FW}^{dq} = \partial \bar{V}(\hat{u}_{s,max}) \cap \bar{T}(m_{m,ref})$$

OFTC with analytical ORCC: Operation strategies

Maximum Torque per Voltage (**MTPV** @ $3.50 \cdot \omega_{m,R}$): Reference torque **not feasible**



Optimization problem

$$\begin{aligned} \max_{\mathbf{i}_s^{dq} \in \bar{F}} & -\|\mathbf{u}_s^{dq}(\mathbf{i}_s^{dq})\|^2 \quad \text{s.t.} \\ & \underbrace{(\mathbf{i}_s^{dq})^\top \bar{\mathbf{T}} \mathbf{i}_s^{dq} + 2 \bar{\mathbf{t}}^\top \mathbf{i}_s^{dq}}_{=m_m(\mathbf{i}_s^{dq})} - m_{m,ref} = 0 \end{aligned}$$

Solution set


$$\overline{\text{MTPV}}(\bar{\mathbf{i}}_s^{dq}, \bar{\omega}_p, \dots) := \left\{ \mathbf{i}_s^{dq} \in \mathbb{R}^2 \mid (\mathbf{i}_s^{dq})^\top \bar{\mathbf{M}}_V \mathbf{i}_s^{dq} + 2 \bar{\mathbf{m}}_V^\top \mathbf{i}_s^{dq} + \bar{\mu}_V = 0 \right\}$$

Optimal reference currents (★)

$$\mathbf{i}_{s,\text{MTPV}}^{dq} = \overline{\text{MTPV}} \cap \partial \bar{V}(\hat{u}_{s,max})$$

OFTC with analytical ORCC: Operation management

Decision tree



OFTC with analytical ORCC: Implementation results

Exemplary laboratory setup


Reluctance SM (RSM) and Permanent-magnet SM



Real-time system and VSIs









Host PC (rapid prototyping)




OFTC with analytical ORCC: Implementation results

RSM (9.6 kW@1 500 rpm): Nonlinear maps of torque, flux linkages and differential inductances




OFTC with analytical ORCC: Implementation results

RSM (9.6 kW@1 500 rpm): Comparison of numerical and analytical solutions for MTPC





Cartesian coordinates



polar coordinates

OFTC with analytical ORCC: Implementation results



RSM (9.6 kW@1 500 rpm): Comparison of computational load (Euler's solution for fourth-order polynomials)



- Execution times for $N = 10^6$ runs (downsampled by factor 100)
- Standard deviations $\sigma_n = 1.61 \cdot 10^{-6} \text{ s}$ and $\sigma_a = 0.73 \cdot 10^{-6} \text{ s}$
- Average execution times $\mu_n = 43.4 \cdot 10^{-6} \text{ s}$ and $\mu_a = 7.23 \cdot 10^{-6} \text{ s}$ (**>6x faster**)



OFTC with analytical ORCC: Implementation results

PME-RSM (4.5 kW@1 500 rpm): Implementation by colleagues [$\max \left(L_s^d(\dot{i}_s^{dq})/L_s^q(\dot{i}_s^{dq}) \right) = 1.43$] [166]










OFTC with analytical ORCC: Implementation results

IPMSM (generator mode): Efficiency enhancements considering iron losses [15]





OFTC with analytical ORCC: Implementation results

IPMSM (3.9 kW@5 500 rpm): Nonlinear maps of torque, flux linkages, differential inductances and iron resistance



OFTC with analytical ORCC: Implementation results

IPMSM (3.9 kW@5 500 rpm): Animation



MTPL [purple]

MC_{ext} [yellow]


MC [orange]

MTPV [blue]

FW [green]

OFTC with analytical ORCC: Implementation results

IPMSM (3.9 kW@5 500 rpm): Comparison of MTPL [■] & MTPC [■] for **four** operating points (OPs)



OP	Speed	Torque
B_{11}	30% $n_{m,R}$	30% $m_{m,R}$
B_{12}	30% $n_{m,R}$	100% $m_{m,R}$
B_{21}	100% $n_{m,R}$	30% $m_{m,R}$
B_{22}	100% $n_{m,R}$	100% $m_{m,R}$


- Copper losses increase with torque
- Iron losses increase with speed *and* torque
- MTPL outperforms MTPC for three OPs (equal for B_{12})
- highest efficiency enhancement for high speeds and low(er) torque (i.e., B_{21} with $\Delta\eta_m > 2\%$)

2 Advanced optimal feedforward torque control (OFTC) and operation management of electrical drives

- Motivation
- Problem statement and proposed solution
- OFTC with analytical ORCC
 - Analytical computation
 - Operation strategies
 - Operation management and decision tree
 - Implementation results
- OFTC with ANN-based ORCC
 - Overview
 - Artificial Neural Network Design
 - Implementation results

OFTC with ANN-based ORCC: Overview

Optimal feedforward torque control (OFTC) with ANN-based ORCC within the control system




TT 04-2 Electrical Machines and Drives (Y405)

Monday, 19 June 2023 @ 17:40-18:00 (ISIE23-000130)

N. Monzen et al, "Artificial neural network based optimal feedforward torque control of electrically excited synchronous machines"

OFTC with ANN-based ORCC: Artificial Neural Network Design


Used ANN topology




$$\hat{\mathbf{y}} = \begin{pmatrix} i_{ref,ANN}^d \\ i_{ref,ANN}^q \end{pmatrix} = \Phi_4 \left(\mathbf{W}_4 \Phi_3 \left(\mathbf{W}_3 \Phi_2 \left(\mathbf{W}_2 \Phi_1 \left(\underbrace{\mathbf{W}_1 \begin{pmatrix} m_{m,ref} \\ \omega_p \\ \hat{i}_{s,max} \\ \hat{u}_{s,max} \end{pmatrix}}_{=\mathbf{x}} + \mathbf{b}_1 \right) + \mathbf{b}_2 \right) \right) + \mathbf{b}_3 \right) + \mathbf{b}_4 \right).$$

OFTC with ANN-based ORCC: Artificial Neural Network Design


Possible and used ANN activation function




(a) Sigmoid.




(b) Tangens hyperbolicus.




(c) Signum (sign).



(d) Identity.




(e) Rectified Linear Unit (ReLU).



(f) Saturation.


OFTC with ANN-based ORCC: Artificial Neural Network Design

ANN training and validation





OFTC with ANN-based ORCC: Artificial Neural Network Design

Estimation accuracy (norm of estimation error) versus floating point operations



OFTC with ANN-based ORCC: Implementation results

Time series



(a) OFTC with analytical ORCC (OFTC_{ANA}).

(b) ANN-based OFTC (OFTC_{ANN}).

Advanced optimal feedforward torque control and operation management of electrical drives


Prof. Dr.-Ing. habil. Christoph M. Hackl

Version from 2023/05/29


47/75

OFTC with ANN-based ORCC: Implementation results


Speed-torque map




(a) Speed-torque map (OFTC_{ANA}).



(b) Speed-torque map (OFTC_{ANN}).



(c) Current locus (OFTC_{ANA}).



(d) Current locus (OFTC_{ANN}).

OFTC with ANN-based ORCC: Implementation results

Performance comparison and execution times

Performance measure	$\mathbf{X=OFTC}_{\text{LUT}}$	$\mathbf{X=OFTC}_{\text{NUM}}$	$\mathbf{X=OFTC}_{\text{ANA}}$	$\mathbf{X=OFTC}_{\text{ANN}}$
$\int i_{s,\text{ref},\text{OFTC}_{\text{NLP}}}^d - i_{s,\text{ref},\text{X}}^d dt$	0.176 As	0.186 As	0.384 As	0.227 As
$\int i_{s,\text{ref},\text{OFTC}_{\text{NLP}}}^q - i_{s,\text{ref},\text{X}}^q dt$	0.195 As	0.207 As	0.256 As	0.213 As
$\int m_{\text{ref},\text{X}} - m_{\text{m}} dt$	0.018 Nms	0.017 Nms	0.026 Nms	0.020 Nms
$\int \hat{u}_{s,\text{max}} - \ \mathbf{u}_{s,\text{ref},\text{X}}^{dq}\ dt$	0.445 Vs	0.446 Vs	0.454 Vs	0.459 Vs
$\int \hat{i}_{s,\text{max}} - \ \mathbf{i}_{s,\text{ref},\text{X}}^{dq}\ dt$	0.010 As	0.000 As	0.000 As	0.059 As
$\int n_{m,\text{ref}} - n_{m,\text{X}} dt$	$752.4 \frac{\text{s}}{\text{min}}$	$750.9 \frac{\text{s}}{\text{min}}$	$752.6 \frac{\text{s}}{\text{min}}$	$757.8 \frac{\text{s}}{\text{min}}$
$\bar{t}_{\text{exec},\text{X}}$	2 734.782 μs	448.745 μs	439.671 μs	5.855 μs

Outline

3 Conclusion

Conclusion

Summary and future work

To take home

- **Unified** framework for OFTC with analytical ORCC for MTPL (MTPC), FW, MC_(ext) & MTPV (MTPF) based on [102, 105, 106, 131, 167] and [168, Chapt. 6.9]
 - **Sequential quadratic optimization problem** (online linearization, iteration, etc.),
 - Finding **intersection point** of two quadrics (ellipses, hyperbolas, etc.)
- **Novel** OFTC with **analytical but ANN-based** ORCC (no decision tree required) [24]
- **Performance aspects** for both approaches:
 - Consideration of $R_s \neq 0$, $R_{s,Fe} \neq 0$ and $L_{s,m} \neq 0$ and current, speed, angle & temperature dependency (all **feasible** and **simultaneously**)
 - **fast(er)** and **more accurate** computation (ANN the fastest)
 - **applicable** in real-world (e.g. nonlinear RSM, PME-RSM or IPMSM; also IMs or DFIMs or EESM)

Future work

- more extensive experimental validation
- impact of (parameter/modelling/alignment) uncertainties
- consideration of *rotor* iron losses (e.g. for IMs), *current transients* and *multi-phase* machines
- combination with minimization of *conduction and switching losses* [169]

References

Journal article (published 2022; see doi: [10.3390/en15051838](https://doi.org/10.3390/en15051838))



energies



Article

Artificial Neural Network Based Optimal Feedforward Torque Control of Interior Permanent Magnet Synchronous Machines: A Feasibility Study and Comparison with the State-of-the-Art

Max A. Buettner[†], Niklas Monzen[†]  and Christoph M. Hackl^{*} 

Department of Electrical Engineering and Information Technology, Hochschule München (HM) University of Applied Sciences, Lothstr. 64, 80335 München, Germany; max.buettner@hm.edu (M.A.B.); niklas.monzen@hm.edu (N.M.)

* Correspondence: christoph.hackl@hm.edu

† These authors contributed equally to this work.

Abstract: A novel Artificial Neural Network (ANN) Based Optimal Feedforward Torque Control (OFTC) strategy is proposed which, after proper ANN design, training and validation, allows to analytically compute the optimal reference currents (minimizing copper and iron losses) for Interior Permanent Magnet Synchronous Machines (IPMSMs) with highly operating point dependent nonlinear electric and magnetic characteristics. In contrast to conventional OFTC, which either utilizes large look-up tables (LUTs; with more than three input parameters) or computes the optimal reference currents numerically or analytically but iteratively (due to the necessary online linearization), the proposed ANN-based OFTC strategy does not require iterations nor a decision tree to find the optimal operation strategy such as e.g., Maximum Torque per Losses (MTPL), Maximum Current (MC) or Field Weakening (FW). Therefore, it is (much) faster and easier to implement while (i) still



Citation: Buettner, M.A.; Monzen, N.; Hackl, C.M. Artificial Neural Network Based Optimal Feedforward Torque Control of Interior Permanent Magnet Synchronous Machines: A Feasibility Study and Comparison with the State-of-the-Art. *Energies* 2022, 15, 1838. <https://doi.org/10.3390/en15051838>

Advanced optimal feedforward torque control and operation management of electrical drives
Prof. Dr.-Ing. habil. Christoph M. Hackl

Version from 2023/05/29

51/75

References

Journal article [105] (published 2017; doi: [10.1080/00207179.2017.1338359](https://doi.org/10.1080/00207179.2017.1338359))

INTERNATIONAL JOURNAL OF CONTROL, 2017
<https://doi.org/10.1080/00207179.2017.1338359>



Taylor & Francis
Taylor & Francis Group

OPEN ACCESS



A unified theory for optimal feedforward torque control of anisotropic synchronous machines

Hisham Eldeeb^a, Christoph M. Hackl^{a,*}, Lorenz Horlbeck^b and Julian Kullick^a

^aResearch Group 'Control of Renewable Energy Systems (CRES)', Munich School of Engineering (MSE), Technical University of Munich (TUM), Munich, Germany; ^bInstitute of Automotive Technology (FTM), Technical University of Munich (TUM), Munich, Germany

ABSTRACT

A unified theory for optimal feedforward torque control of anisotropic synchronous machines with *non-negligible stator resistance* and *mutual inductance* is presented which allows to *analytically* compute (1) the optimal direct and quadrature reference currents for all operating strategies, such as maximum torque per current (MTPC), maximum current, field weakening, maximum torque per voltage (MTPV) or maximum torque per flux (MTPF), and (2) the transition points indicating when to switch between the operating strategies due to speed, voltage or current constraints. The analytical solutions allow for an (almost) instantaneous selection and computation of actual operation strategy and corresponding reference currents. Numerical methods (approximating these solutions only) are *no longer* required. The unified theory is based on one simple idea: all optimisation problems, their respective constraints and the computation of the intersection point(s) of voltage ellipse, current circle or torque, MTPC, MTPV, MTPF hyperbolas are reformulated implicitly as *quadratics* which allows to invoke the Lagrangian formalism and to find the roots of fourth-order polynomials analytically. The proposed theory is suitable for any anisotropic synchronous machine. Implementation and measurement results illustrate effectiveness and applicability of the theoretical findings in real world.

ARTICLE HISTORY

Received 18 March 2017

Accepted 31 May 2017

KEYWORDS

Maximum torque per ampere (MTPA); maximum torque per current (MTPC); maximum torque per voltage (MTPV); maximum torque per flux (MTPF); maximum current (MC); field weakening (FW); analytical solution; optimal feedforward torque control; efficiency; copper losses; anisotropy; synchronous machine; interior

References

Conference publication (published in ICIT 2021 proceedings; see doi: [10.1109/icit46573.2021.9453497](https://doi.org/10.1109/icit46573.2021.9453497))

Generic loss minimization for nonlinear synchronous machines by analytical computation of optimal reference currents considering copper and iron losses

Christoph Hackl, Julian Kullick and Niklas Monzen

Laboratory for Mechatronic and Renewable Energy Systems (LMRES)

Munich University of Applied Sciences (MUAS)

Munich, Germany

{christoph.hackl, julian.kullick, niklas.monzen}@hm.edu

Abstract—The unified theory introduced in [1] allows to solve *analytically* the optimal feedforward torque control (OFTC) problem of anisotropic synchronous machines (SMs). In this paper, the theory is extended by considering relevant machine nonlinearities and incorporating copper and iron losses, thus minimizing the overall (steady-state) losses in the machine. Instead of the well known maximum torque per current (MTPC) operation strategy, *maximum torque per losses (MTPL)* is realized. The unified theory for the derivation of the analytical solution is briefly recapitulated. Moreover, current and speed dependent iron losses, as well as magnetic saturation and cross-coupling effects are considered. The resulting nonlinear optimization problem is solved via online linearization of the relevant expressions

for synchronous machines (SMs) with anisotropic rotor designs, e.g. interior permanent magnet synchronous machines (IPMSMs), reluctance synchronous machines (RSMs) or PM-assisted RSMs (PMA-RSMs), efficiency can be increased by optimal feedforward torque control (OFTC) [3, 4].

The main idea of OFTC is to exploit the ambiguity in the selection of the stator current's *direct* and *quadrature* components (producing the same amount of torque), such that losses are minimized while physical constraints are satisfied (e.g. current or voltage limits). Depending on the actual operating conditions, different optimization problems may be formulated

Advanced optimal feedforward torque control and operation management of electrical drives

Prof. Dr.-Ing. habil. Christoph M. Hackl

References

Conference publication (published in ISIE 2021 proceedings; see doi: [10.1109/ISIE45552.2021.9576186](https://doi.org/10.1109/ISIE45552.2021.9576186))

Optimal feedforward torque control for nonlinear induction machines considering stator & rotor copper losses and current & voltage limits

Andre Thommessen, Christoph Hackl

Laboratory for Mechatronic and Renewable Energy Systems (LMRES)

Munich University of Applied Sciences (MUAS)

Munich, Germany

{andre.thommessen, christoph.hackl}@hm.edu

Abstract—In order to *analytically* solve the optimal feedforward torque control (OFTC) problem of induction machines (IMs), the unified theory for synchronous machine introduced in [1] is extended by considering relevant IM *nonlinearities* and incorporating stator and rotor copper losses. Instead of the well known *Maximum Torque per (stator) Current* (MTPC) operation strategy, *Maximum Torque per (copper) Losses* (MTPL_{Cu}) is realized and extended by the *Maximum (rotor) Current* (MC_{r,ext}) strategy due to stator and rotor current limitations. Modeling magnetic saturation and cross-coupling effects leads to a constrained *nonlinear* optimization problem which is solved based on the idea of *sequential quadratic programming* (SQP). The second order Taylor approximations are formulated in implicit

generic approach can also be applied to other types of inverter-fed IMs, such as squirrel-cage induction machines (SCIMs).

The highest priority of the OFTC is to provide the reference torque while minimizing losses. In a wide operating range, there usually exist (infinitely many) different combinations of reference currents resulting in the same torque. Thus, an optimal reference current computation (ORCC) is desirable which minimizes the current-dependent IM losses while reaching the reference torque and taking into account operating (e.g. current & voltage) limits. To do so, this paper proposes a physics-based nonlinear IM model for analytical ORCC

Advanced optimal feedforward torque control and operation management of electrical drives

Prof. Dr.-Ing. habil. Christoph M. Hackl

Version from 2023/05/29

54/75

References

Chapter 6.9 in [168] (published in 2020 in Schröder “Elektrische Antriebssysteme”; doi: [10.1007/978-3-662-62700-6](https://doi.org/10.1007/978-3-662-62700-6))





Abb. 6.101 Wirkungsweise der Feldschwächregelung mit Spannungsrückkopplung

6.9 Optimale Betriebsführung von nichtlinearen Synchronmaschinen

C. M. Hackl, J. Kullick, N. Monzen

Der folgende Abschnitt basiert auf den Publikationen [HH16; Eld+16; EHK16; Eld+17b; Hac+17; Eld+17a]. Darin wurde die erste allgemeine Theorie zur analytischen Berechnung der optimalen (verlustminimierenden) Sollströme für anisotrope Synchronmaschinen mit konstanter Erregung vorgestellt. Die weithin verbreiteten und vereinfachten Annahmen wie z. B. die Vernachlässigung des Statorwiderstandes oder der magnetischen Kreuzkopplung konnten aufgehoben werden. Zusätzlich erlaubt die Theorie die Berücksichtigung von Eisenverlusten und Nicht-

References

Monograph [46] (published May 2017; doi: [10.1007/978-3-319-55036-7](https://doi.org/10.1007/978-3-319-55036-7))



References I

- [1] Christoph M. Hackl. A physics-based model of electro-active polymer actuators as the bases for a Gopinath-style motion state observer. Bachelorthesis, Lehrstuhl für Elektrische Antriebssysteme, Technische Universität München, Germany & Department of Mechanical Engineering and Department of Electrical & Computer Engineering, University of Wisconsin-Madison, USA, 2003.
- [2] Christoph Hackl, H.-Y. Tang, R.D. Lorenz, L.-S. Turng, and Dierk Schröder. A multiphysics model of planar electro-active polymer actuators. In *Conference Record of the 39th IEEE Industrial Application Society Annual Meeting*, volume 3, pages 2125–2130. Institute of Electrical and Electronics Engineers (IEEE), 2004.
- [3] Christoph Hackl, H.-Y. Tang, R.D. Lorenz, L.-S. Turng, and Dierk Schröder. A multidomain model of planar electro-active polymer actuators. *IEEE Transactions on Industry Applications*, 41(5):1142–1148, sep 2005.
- [4] Christoph M. Hackl and Beatrix Mair. Optimale Bahnzugregelung am Beispiel einer Papierstreicheanlage. In *Konferenzband des 9. Bahnlaufseminar*, TU Chemnitz, Deutschland, 2007.
- [5] Christoph M. Hackl and Beatrix Mair. Optimierung der Bahnspannungsregelung durch dezentrale Regelsysteme auf der Basis von moderner Mikroelektronik und intelligenter Software zur Steigerung der Produktionssicherheit und der Produktivität von Papierstreicheanlagen. Abschlussbericht zum Forschungsvorhaben AiF/IGF 14140N, Arbeitsgemeinschaft industrieller Forschungsvereinigungen “Otto von Guericke” (AiF), 2007.
- [6] Beatrix Mair and Christoph M. Hackl. Optimierung der Bahnspannungsregelung durch dezentrale Regelsysteme auf der Basis von moderner Mikroelektronik und intelligenter Software zur Steigerung der Produktionssicherheit und der Produktivität von Papierstreicheanlagen. PTS Forschungsbericht, The Paper Technology Specialists, Hessestr. 134, 80797 München, Germany, 2007.
- [7] Christoph M. Hackl and Beatrix Mair. Besser Bahnen ziehen – Optimale Bahnzugregelung mit dSPACE-Prototyping-System. *dSPACE Magazine*, 2:40–45, 2008.
- [8] Christoph M. Hackl and Beatrix Mair. Smoothing the tension - optimal web tension control with a dSPACE prototyping system. *dSPACE Magazine*, 2:40–45, 2008.
- [9] Christian Endisch, Christoph Hackl, and Dierk Schröder. Optimal brain surgeon for general dynamic neural networks. In José Neves, Manuel Filipe Santos, and José Manuel Machado, editors, *Progress in Artificial Intelligence*, volume 4974/2007 of *Lecture Notes in Artificial Intelligence*, pages 15–28. Springer-Verlag, Berlin, 2007.

References II

- [10] Christian Endisch, Christoph Hackl, and Dierk Schröder. System identification with general dynamic neural networks and network pruning. *International Journal of Computational Intelligence*, 4(3):187–195, 2007.
- [11] Christian. Endisch, Peter Stolze, Peter Endisch, Christoph M.. Hackl, and Ralph M. Kennel. Levenberg-Marquardt-based OBS algorithm using adaptive pruning interval for system identification with dynamic neural networks. In *Proceedings of the IEEE International Conference on Systems, Man and Cybernetics*, pages 3402–3408, San Antonio, TX, USA, oct 2009. Institute of Electrical and Electronics Engineers (IEEE).
- [12] C. Endisch, P. Stolze, C. Hackl, and D. Schröder. Comments on “Backpropagation algorithms for a broad class of dynamic networks”. *IEEE Transactions on Neural Networks*, 20(3):540–541, mar 2009.
- [13] Mohamed Abdelrahem, Christoph Hackl, and Ralph Kennel. Application of extended kalman filter to parameter estimation of doubly-fed induction generators in variable-speed wind turbine systems. In *2015 International Conference on Clean Electrical Power (ICCEP)*. IEEE.
- [14] Christoph M. Hackl. Speed funnel control with disturbance observer for wind turbine systems with elastic shaft. In *Proceedings of the 54th IEEE Conference on Decision and Control (CDC 2015)*, pages 2005–2012, Osaka, Japan, 2015.
- [15] Simon Krüner and Christoph M. Hackl. Experimental identification of the optimal current vectors for a permanent-magnet synchronous machine in wave energy converters. *Energies*, 12(862), 2019.
- [16] Christoph M. Hackl and Markus Landerer. A unified method for online detection of phase variables and symmetrical components of unbalanced three-phase systems with harmonic distortion. *Energies*, 12(17), 2019.
- [17] Mohamed Abdelrahem, Ralph Kennel, Christoph Hackl, Mehmet Dal, and José Rodríguez. Efficient finite-position-set mras observer for encoder-less control of dfigs. In *2019 IEEE International Symposium on Predictive Control of Electrical Drives and Power Electronics (PRECEDE)*, pages 1–6, May 2019.
- [18] Christoph M. Hackl and Markus Landerer. A unified method for generic signal parameter estimation of arbitrarily distorted single-phase grids with dc-offset. *IEEE Open Journal of the Industrial Electronics Society*, 1:235–246, 2020.

References III

- [19] T. Kreppel, F. Rojas, C. M. Hackl, O. Kalmbach, M. Díaz, and G. Gatica. Extended Model of Chopper Cells for Open Circuit Fault Detection in Modular Multilevel Cascade Converters using Sliding Mode Observers. In *2020 IEEE 11th International Symposium on Power Electronics for Distributed Generation Systems (PEDG)*, pages 487–493, 2020. ISSN: 2329-5767.
- [20] Mostafa Ahmed, Mohamed Abdelrahem, Ralph Kennel, and Christoph M. Hackl. A robust maximum power point tracking based model predictive control and extended kalman filter for pv systems. In *2020 International Symposium on Power Electronics, Electrical Drives, Automation and Motion (SPEEDAM)*, pages 514–519, 2020.
- [21] Mostafa Ahmed, Mohamed Abdelrahem, Ralph Kennel, and Christoph M. Hackl. Maximum power point tracking based model predictive control and extended kalman filter using single voltage sensor for pv systems. In *2020 IEEE 29th International Symposium on Industrial Electronics (ISIE)*, pages 1039–1044, 2020.
- [22] Christoph M. Hackl and Markus Landerer. Modified second-order generalized integrators with modified frequency locked loop for fast harmonics estimation of distorted single-phase signals. *IEEE Transactions on Power Electronics*, 2020.
- [23] Julian Kullick and Christoph M Hackl. Nonlinear modeling, identification and optimal feedforward torque control of induction machines using steady-state machine maps. *IEEE Transactions on Industrial Electronics*, pages 1–1, 2022.
- [24] Max A. Buettner, Niklas Monzen, and Christoph M. Hackl. Artificial neural network based optimal feedforward torque control of interior permanent magnet synchronous machines: A feasibility study and comparison with the state-of-the-art. *Energies*, 15(5):1838, 2022.
- [25] Shih-Wei Su, Christoph M. Hackl, and Ralph Kennel. Analytical prototype functions for flux linkage approximation in synchronous machines. *IEEE Open Journal of the Industrial Electronics Society*, 3:265–282, 2022.
- [26] Shih-Wei Su, Hannes Börngen, Christoph M. Hackl, and Ralph Kennel. Nonlinear current control of reluctance synchronous machines with analytical flux linkage prototype functions. *IEEE Open Journal of the Industrial Electronics Society*, pages 1–12.
- [27] Christoph M. Hackl. *Contributions to High-gain Adaptive Control in Mechatronics*. PhD thesis, Lehrstuhl für Elektrische Antriebssysteme und Leistungselektronik, Technische Universität München (TUM), Germany, 2012.

References IV

- [28] Christoph M. Hackl. Dynamische Reibungsmodellierung: Das Lund-Grenoble (LuGre) Reibmodell. In Dierk Schröder, editor, *Elektrische Antriebe – Regelung von Antriebssystemen*, chapter 25, pages 1615–1657. Springer-Verlag, 2015.
- [29] Christoph M. Hackl. Dynamische Reibungsmodellierung: Das Lund-Grenoble (LuGre) Reibmodell. In Dierk Schröder, editor, *Elektrische Antriebe – Regelung von Antriebssystemen*, chapter 9.4, pages 1315–1357. Springer-Verlag.
- [30] Hans Schuster, Christoph Michael Hackl, Christian Westermaier, and Dierk Schröder. Funnel-control for electrical drives with uncertain parameters. In *Proceedings of the 7th International Power Engineering Conference*, Singapore, 2005.
- [31] Christoph M. Hackl and Dierk Schröder. Extension of high-gain controllable systems for improved accuracy. In *Proceedings of the 2006 IEEE International Conference on Control Applications (CCA 2006)*, pages 2231–2236, Munich, Germany, oct 2006. Institute of Electrical and Electronics Engineers (IEEE).
- [32] Christoph Michael Hackl and Dierk Schröder. Funnel-control for nonlinear multi-mass flexible systems. In *Proceedings of the 32nd Annual Conference on IEEE Industrial Electronics*, pages 4707–4712, Paris, France, 2006.
- [33] Christoph M. Hackl, Hans Schuster, Christian Westermaier, and Dierk Schröder. Funnel-control with integrating prefilter for nonlinear, time-varying two-mass flexible servo systems. In *Proceedings of the 9th International Workshop on Advanced Motion Control*, pages 456–461, Istanbul, Turkey, 2006. Institute of Electrical and Electronics Engineers (IEEE).
- [34] Christoph M. Hackl, Yang Ji, and Dierk Schröder. Enhanced funnel-control with improved performance. In *Proceedings of the 15th Mediterranean Conference on Control and Automation*, pages Paper T01–016, Athens, Greece, jun 2007. Institute of Electrical and Electronics Engineers (IEEE).
- [35] Christoph M. Hackl, Yang Ji, and Dierk Schröder. Funnel-control with constrained control input compensation. In *Proceedings of the 9th IASTED International Conference CONTROL AND APPLICATIONS*, pages 147–152, Montreal, Quebec, Canada, 2007.
- [36] Christoph M. Hackl, Yang Ji, and Dierk Schröder. Nonidentifier-based adaptive control with saturated control input compensation. In *Proceedings of the 15th Mediterranean Conference on Control and Automation*, pages Paper T01–15, Athens, Greece, jun 2007. Institute of Electrical and Electronics Engineers (IEEE).

References V

- [37] Christoph M. Hackl and Dierk Schröder. Funnel-control with online foresight. In *Proceedings of the 26th IASTED International Conference MODELLING, IDENTIFICATION AND CONTROL*, pages 171–176, Innsbruck, Austria, 2007.
- [38] Christoph M. Hackl and Dierk Schröder. Non-identifier based adaptive control in robotics: An introduction. *International Journal of Factory Automation, Robotics and Soft Computing*, 4:90–99, 2008.
- [39] Christoph M. Hackl, Christian Endisch, and Dierk Schröder. Specially designed funnel-control in mechatronics. In *Proceedings of the 5th International Conference on Computational Intelligence, Robotics and Autonomous Systems*, pages 59–64, 2008.
- [40] Christoph M. Hackl, Christian Endisch, and Dierk Schröder. Contributions to non-identifier based adaptive control in mechatronics. *Robotics and Autonomous Systems, Elsevier*, 57(10):996–1005, 2009.
- [41] Christoph M. Hackl. Funnel Control: Implementierung, Erweiterung und Anwendung. In Dierk Schröder, editor, *Intelligente Verfahren: Systemidentifikation und Regelung nichtlinearer Systeme*, pages 697–760. Springer-Verlag, Berlin, 2010.
- [42] Christoph M. Hackl and Stephan Trenn. The bang-bang funnel controller: An experimental verification. *PAMM*, 12(1):735–736, dec 2012.
- [43] Christoph M. Hackl, Norman Hopfe, Achim Ilchmann, Markus Mueller, and Stephan Trenn. Funnel control for systems with relative degree two. *SIAM Journal on Control and Optimization*, 51(2):965–995, jan 2013.
- [44] Christoph M. Hackl. Funnel control for wind turbine systems. In *Proceedings of the 2014 IEEE International Conference on Control Applications (CCA 2014)*, pages 1377–1382, Antibes, France, oct 2014. Institute of Electrical and Electronics Engineers (IEEE).
- [45] Christoph M. Hackl. Current PI-funnel control with anti-windup for synchronous machines. In *Proceedings of the 54th IEEE Conference on Decision and Control (CDC 2015)*, pages 1997–2004, Osaka, Japan, dec 2015. Institute of Electrical and Electronics Engineers (IEEE).
- [46] Christoph M. Hackl. *Non-identifier based adaptive control in mechatronics: Theory and Application*. Number 466 in Lecture Notes in Control and Information Sciences. Springer International Publishing, Berlin, 2017.
- [47] Christoph M. Hackl, Christian Endisch, and Dierk Schröder. Applicability of funnel-control in robotics. In *Proceedings of the 5th International Conference on Computational Intelligence, Robotics and Autonomous Systems*, pages 65–70, Linz, Austria, 2008.

References VI

- [48] Christoph M. Hackl, Christian Endisch, and Dierk Schröder. Funnel-control in robotics: An introduction. In *Proceedings of the 16th Mediterranean Conference on Control and Automation*, pages 913–919, Ajaccio, France, jun 2008. Institute of Electrical and Electronics Engineers (IEEE).
- [49] Christoph M. Hackl and Dierk Schröder. Non-identifier based adaptive control in robotics: An introduction. In Salvatore Pennacchio, editor, *Recent advances in Control Systems, Robotics and Automation*, volume 1. INTERNATIONALSAR International Society for Advanced Research, Palermo, Italy, third edition, 2009.
- [50] Christoph M. Hackl. High-gain adaptive position control. *International Journal of Control*, 84(10):1695–1716, oct 2011.
- [51] Christoph M. Hackl, Andreas G. Hofmann, Rik W. De Doncker, and Ralph M. Kennel. Funnel control for speed & position control of electrical drives: A survey. In *Proceedings of the 19th Mediterranean Conference on Control & Automation (MED)*, pages 181–188, Corfu Island, Greece, jun 2011. Institute of Electrical and Electronics Engineers (IEEE).
- [52] Christoph M. Hackl, Andreas G. Hofmann, and Ralph M. Kennel. Funnel control in mechatronics: An overview. In *Proceedings of the 50th IEEE Conference on Decision and Control (CDC) and European Control Conference (ECC)*, pages 8000–8007, Orlando, FL, USA, dec 2011. Institute of Electrical and Electronics Engineers (IEEE).
- [53] Christoph M. Hackl. ‘Funnel control’ zur Positionsregelung von starren Drehgelenkrobotern mit grob bekannter Trägheitsmatrix. In *Tagungsband des GMA-Fachausschuss 1.40*, pages 302–310, Anif, Austria, 2012.
- [54] Christoph M. Hackl and Ralph M. Kennel. Position funnel control for rigid revolute joint robotic manipulators with known inertia matrix. In *Proceedings of the 20th Mediterranean Conference on Control and Automation*, pages 615–620, Barcelona, Spain, jul 2012. Institute of Electrical and Electronics Engineers (IEEE).
- [55] Christoph M. Hackl and Ralph M. Kennel. Position funnel control with linear internal model. In *Proceedings of 2012 IEEE International Conference on Control Applications (CCA 2012)*, pages 1334–1339, Dubrovnik, Croatia, oct 2012. Institute of Electrical and Electronics Engineers (IEEE).
- [56] Timm Faulwasser and Christoph M. Hackl. Path-following funnel control for rigid-link revolute-joint robotic systems. In *Proceedings of the 21st International Symposium on Mathematical Theory of Networks and Systems*, pages 1044–1051, Groningen, Netherlands, 2014.

References VII

- [57] Julian Kullick and Christoph Hackl. Dynamic Modeling and Simulation of Deep Geothermal Electric Submersible Pumping Systems. *Energies*, 10(10):1659, October 2017.
- [58] Florian Bauer, Christoph M. Hackl, Keyue Ma Smedley, and Ralph M. Kennel. Multicopter with series connected propeller drives. *IEEE Transactions on Control Systems Technology*, pages 1–12, 2017.
- [59] Christoph M. Hackl, Florian Larcher, Alexander Döttinger, and Ralph M. Kennel. Is multiple-objective model-predictive control “optimal”? In *Proceedings of the 2013 IEEE International Symposium on Predictive Control of Electrical Drives and Power Electronics (PRECEDE 2013)*, pages 1–8, Munich, Germany, oct 2013. Institute of Electrical and Electronics Engineers (IEEE).
- [60] Z. Zhang, C. Hackl, F. Wang, Z. Chen, and R. Kennel. Encoderless model predictive control of back-to-back converter direct-drive permanent-magnet synchronous generator wind turbine systems. In *Proceedings of 15th European Conference on Power Electronics and Applications*, pages 1–10. Institute of Electrical and Electronics Engineers (IEEE), sep 2013.
- [61] Mohamed Abdelrahman, Christoph M. Hackl, and Ralph Kennel. Sensorless control of doubly-fed induction generators in variable-speed wind turbine systems. In *Proceedings of the 5th International Conference on Clean Electrical Power (ICCEP)*, pages 423–430, Taormina, Italy, jun 2015. Institute of Electrical and Electronics Engineers (IEEE).
- [62] Christian Dirscherl, Josef Fessler, Christoph Hackl, and Hanka Ipach. State-feedback control and observer design of grid-connected power inverters with LCL-filter. In *Proceedings of the 5th Colloquium of the Munich School of Engineering*, Garching, Germany, 2015.
- [63] Christian Dirscherl, Josef Fessler, Christoph M. Hackl, and Hanka Ipach. State-feedback controller and observer design for grid-connected voltage source power converters with LCL-filter. In *Proceedings of the 2015 IEEE International Conference on Control Applications (CCA 2015)*, pages 215–222, Sydney, Australia, sep 2015. Institute of Electrical and Electronics Engineers (IEEE).
- [64] Christian Dirscherl, Christoph Hackl, and Korbinian Schechner. Explicit model predictive control with disturbance observer for grid-connected voltage source power converters. In *Proceedings of the 2015 IEEE International Conference on Industrial Technology (ICIT 2015)*, pages 999–1006. Institute of Electrical and Electronics Engineers (IEEE), mar 2015.

References VIII

- [65] Christian Dirscherl, Christoph M. Hackl, and Korbinian Schechner. Pole-placement based nonlinear state-feedback control of the DC-link voltage in grid-connected voltage source power converters: A preliminary study. In *Proceedings of the 2015 IEEE International Conference on Control Applications (CCA 2015)*, pages 207–214, Sydney, Australia, sep 2015. Institute of Electrical and Electronics Engineers (IEEE).
- [66] Christoph M. Hackl. MPC with analytical solution and integral error feedback for LTI MIMO systems and its application to current control of grid-connected power converters with LCL-filter. In *Proceedings of the 2015 IEEE International Symposium on Predictive Control of Electrical Drives and Power Electronics (PRECEDE 2015)*, pages 61–66, Valparaiso, Chile, oct 2015. Institute of Electrical and Electronics Engineers (IEEE).
- [67] Zhenbin Zhang, Hue Xu, M. Xue, Z. Chen, T. Sun, Ralph Kennel, and Christoph Hackl. Predictive control with novel virtual flux estimation for back-to-back power converters. *IEEE Transactions on Industrial Electronics*, 62(5):2823–2834, may 2015.
- [68] Ayman Ayad, Mohamed Hashem, Christoph Hackl, and Ralph Kennel. Proportional-resonant controller design for quasi-Z-source inverters with LC filters. In *Proceedings of the 42nd IEEE Industrial Electronics Conference (IECON 2016)*, Firenze, Italy, 2016.
- [69] Christoph M. Hackl. On the equivalence of proportional-integral and proportional-resonant controllers with anti-windup. *arXiv:1610.07133*, 2016.
- [70] Josh C. Mitchell, Maarten J. Kamper, and Christoph M. Hackl. Small-scale reluctance synchronous generator variable speed wind turbine system with DC transmission linked inverters. In *Proceedings of the IEEE Energy Conversion Congress & Exposition (ECCE)*, Milwaukee, WI, USA, 2016.
- [71] Zhenbin Zhang, Christoph Hackl, Mohamed Abdelrahman, and Ralph Kennel. Voltage sensorless direct model predictive control of 3L-NPC back-to-back power converter PMSG wind turbine systems with fast dynamics. In *Proceedings of the Power Electronics Student Summit (PESS 2016)*, Aachen, Germany, 2016.
- [72] Zhenbin Zhang, Christoph Hackl, and Ralph Kennel. Computationally efficient DMPC for three-level NPC back-to-back converters in wind turbine systems with PMSG. *IEEE Transactions on Power Electronics*, 32:8018–8034, 2017.
- [73] Zhenbin Zhang, Christoph Hackl, and Ralph Kennel. FPGA based direct model predictive current control of PMSM drives with 3L-NPC power converters. In *Proceedings of the PCIM Europe 2016*, 2016.

References IX

- [74] Zhenbin Zhang, Ralph Kennel, and Christoph Hackl. Computationally efficient direct model predictive control for three-level NPC back-to-back converter PMSG wind turbine systems. In *Proceedings of the 2016 International Symposium on Power Electronics, Electrical Drives, Automation and Motion (SPEEDAM 2016)*, pages 1045–1050, Anacapri, Italy, jun 2016. Institute of Electrical and Electronics Engineers (IEEE).
- [75] Zhenbin Zhang, Ralph Kennel, and Christoph M. Hackl. Performance-enhanced direct multiple-vector model predictive power control for grid-tied AFEs. In *Proceedings of the 2016 IEEE 8th International Power Electronics and Motion Control Conference (IPEMC-ECCE Asia)*, pages 2904–2909, Hefei, China, may 2016. Institute of Electrical and Electronics Engineers (IEEE).
- [76] Mohamed Abdelrahman, Christoph Michael Hackl, and Ralph Kennel. Finite set model predictive control with on-line parameter estimation for active frond-end converters. *Electrical Engineering*, 100(3):1497–1507, Sep 2018.
- [77] M. Espinoza, R. Cardenas, J. C. Clare, D. Soto, M. Diaz, E. Espina, and C. M. Hackl. An integrated converter and machine control system for mmc-based high power drives. *IEEE Transactions on Industrial Electronics*, PP(99):1–1, 2018.
- [78] Christoph M. Hackl, Urs Pecha, and Korbinian Schechner. Modeling and control of permanent-magnet synchronous generators under open-switch converter faults. *IEEE Transactions on Power Electronics*, 2018.
- [79] Korbinian Schechner, Florian Bauer, and Christoph M. Hackl. Nonlinear DC-link PI control for airborne wind energy systems during pumping mode. In Roland Schmehl, editor, *Airborne Wind Energy: Advances in Technology Development and Research*. Springer Singapore, 2019.
- [80] M. Diaz, R. Cardenas, M. Espinoza, C. M. Hackl, F. Rojas, J. C. Clare, and P. Wheeler. Vector control of a modular multilevel matrix converter operating in the full output-frequency range. *IEEE Transactions on Industrial Electronics*, 66(7):5102–5114, July 2019.
- [81] Michael Saegmueller, Christoph Hackl, Rolf Witzmann, and Rene Richter. Analytic solutions for minimum conduction loss modulation of dual active bridge converters including frequency variation. In *IECON 2020 The 46th Annual Conference of the IEEE Industrial Electronics Society*. IEEE, oct 2020.
- [82] O. Kalmbach, C. M. Hackl, and F. Rojas. A Generic Switching State-Space Model for Modular Multilevel Cascade Converters. In *2020 IEEE 11th International Symposium on Power Electronics for Distributed Generation Systems (PEDG)*, pages 447–454, 2020. ISSN: 2329-5767.

References X

- [83] Oliver Kalmbach, Christian Dirscherl, and Christoph M. Hackl. Discrete-Time DC-Link Voltage and Current Control of a Grid-Connected Inverter with LCL-Filter and Very Small DC-Link Capacitance. *Energies*, 13(21):5613, 2020.
- [84] Mostafa Ahmed, Mohamed Abdelrahem, Ralph Kennel, and Christoph M. Hackl. An enhanced maximum power point tracking based finite-control-set model predictive control for pv systems. In *2020 11th Power Electronics, Drive Systems, and Technologies Conference (PEDSTC)*, pages 1–6, 2020.
- [85] Michael Saegmueller, Christoph Hackl, Rolf Witzmann, and René Richter. Analytic solutions for full operating range single-side zvs modulation of dual active bridge converters. In *Proceedings of the IEEE International Symposium on Industrial Electronics (ISIE) 2021*. IEEE, 2021.
- [86] Christoph Hackl, Simon Krüner, and Zhao Song. 3d-modulation and pi state-feedback control for voltage source inverters with split dc-link. In *Proceedings of the IEEE International Symposium on Industrial Electronics (ISIE) 2021*. IEEE, 2021.
- [87] Christoph Hackl, Christian Dirscherl, and Korbinian Schechner. Modellierung und Regelung von Windkraftanlagen (see <https://arxiv.org/abs/1703.08661> for the english translation). In Dierk Schröder, editor, *Elektrische Antriebe – Regelung von Antriebssystemen*, chapter 10.3, pages 1504–1585. Springer-Verlag, 2021.
- [88] Ibrahim Harbi, Mostafa Ahmed, Christoph M. Hackl, Ralph Kennel, and Mohamed Abdelrahem. A nine-level split-capacitor active-neutral-point-clamped inverter and its optimal modulation technique. *IEEE Transactions on Power Electronics*, 37(7):8045–8064, 2022.
- [89] Christoph M. Hackl, Christian Endisch, and Dierk Schröder. Error reference control of nonlinear two-mass flexible servo systems. In *Proceedings of the 16th Mediterranean Conference on Control and Automation*, pages 1047–1053, Ajaccio, France, jun 2008. Institute of Electrical and Electronics Engineers (IEEE).
- [90] Peter Landsmann, Christoph M. Hackl, and Ralph M. Kennel. Eliminating all machine parameters in encodersless predictive torque control without signal injection. In *Proceedings of the 2011 IEEE International Electric Machines and Drives Conference*, pages 1259–1264. Institute of Electrical and Electronics Engineers (IEEE), may 2011.

References XI

- [91] Christoph M. Hackl. Funnel control with disturbance observer for two-mass systems. In *Proceedings of the 52nd IEEE Conference on Decision and Control (CDC)*, pages 6244–6249, Florence, Italy, dec 2013. Institute of Electrical and Electronics Engineers (IEEE).
- [92] Christoph M. Hackl. PI-funnel control with Anti-windup and its application for speed control of electrical drives. In *Proceedings of the 52nd IEEE Conference on Decision and Control (CDC)*, pages 6250–6255, Florence, Italy, dec 2013. Institute of Electrical and Electronics Engineers (IEEE).
- [93] Christian Dirscherl, Christoph M. Hackl, and Korbinian Schechner. Modeling and control of wind turbine systems with permanent-magnet synchronous generators (PMSG) and doubly fed induction generators (DFIG). In *Proceedings of the 4th Colloquium of the Munich School of Engineering*, Garching, Germany, 2014.
- [94] Christoph M. Hackl. Klein-Windkraftanlagen mit effizienter und kostengünstiger Generatortopologie für Micro-Grids: Eine Voruntersuchung. In *Poster auf der Jahresversammlung des Bundes der Freunde der Technischen Universität München e. V.*, Munich, Germany, 2014.
- [95] Christoph Hackl and Korbinian Schechner. Non-ideal torque control in wind turbine systems: Causes and impacts. In *Proceedings of the 5th Colloquium of the Munich School of Engineering*, Garching, Germany, 2015.
- [96] Christoph M. Hackl, Maarten J. Kamper, Julian Kullick, and Joshua Mitchell. Nonlinear PI current control of reluctance synchronous machines. 2015.
- [97] Christoph M. Hackl and Korbinian Schechner. Non-ideal torque control in wind turbine systems: Causes and impacts. In *Proceedings of the 5th MSE-Kolloquium on “Innovations for Energy Systems, Mobility, Buildings and Materials”*, Munich, Germany, 2015.
- [98] Mohamed Abdelrahem, Christoph M. Hackl, and Ralph Kennel. Encoderless model predictive control of doubly-fed induction generators in variable-speed wind turbine systems. In *Proceedings of the 6th edition of the conference “The Science of Making Torque from Wind” (TORQUE 2016)*, Open access Journal of Physics: Conference Series 753 (2016) 112005, Munich, Germany, 2016.

References XII

- [99] Hisham Eldeeb, Christoph M. Hackl, Lorenz Horlbeck, and Julian Kullick. On the optimal feedforward torque control problem of anisotropic synchronous machines: Quadrics, quartics and analytical solutions. 2016.
- [100] Hisham Eldeeb, Christoph M. Hackl, and Julian Kullick. Efficient operation of anisotropic synchronous machines for wind energy systems. In *Proceedings of the 6th edition of the conference "The Science of Making Torque from Wind" (TORQUE 2016)*, Open access Journal of Physics: Conference Series 753 (2016) 112005, Munich, Germany, 2016.
- [101] Christoph M. Hackl, Maarten J. Kamper, Julian Kullick, and Joshua Mitchell. Current control of reluctance synchronous machines with online adjustment of the controller parameters. In *Proceedings of the 2016 IEEE International Symposium on Industrial Electronics (ISIE 2016)*, pages 153–160, Santa Clara, CA, USA, jun 2016. Institute of Electrical and Electronics Engineers (IEEE).
- [102] Lorenz Horlbeck and Christoph M. Hackl. Analytical solution for the MTPV hyperbola including the stator resistance. In *Proceedings of the IEEE International Conference on Industrial Technology (ICIT 2016)*, pages 1060–1067, Taipei, Taiwan, mar 2016. Institute of Electrical and Electronics Engineers (IEEE).
- [103] Zhenbin Zhang, Ralph Kennel, and Christoph M. Hackl. Two direct torque and power control methods for back-to-back power converter PMSG wind turbine systems. In *Proceedings of the 2016 IEEE 8th International Power Electronics and Motion Control Conference (IPEMC-ECCE Asia)*, pages 1515–1520, Hefei, China, may 2016. Institute of Electrical and Electronics Engineers (IEEE).
- [104] Mohamed. Abdelrahem, Christoph Hackl, and Ralph Kennel. Finite Position Set-Phase Locked Loop for Sensorless Control of Direct-Driven Permanent-Magnet Synchronous Generators. *IEEE Transactions on Power Electronics*, PP(99):1–1, 2017.
- [105] Hisham Eldeeb, Christoph M. Hackl, Lorenz Horlbeck, and Julian Kullick. A unified theory for optimal feedforward torque control of anisotropic synchronous machines. *International Journal of Control*, 2017.
- [106] Hisham Eldeeb, Christoph M. Hackl, Lorenz Horlbeck, and Julian Kullick. Analytical solutions for the optimal reference currents for MTPC/MTPA, MTPV and MTPF control of anisotropic synchronous machines. In *Proceedings of the IEEE International Electric Machines & Drives Conference (IEMDC 2017)*, pages 1–6, Miami, FL, USA, 2017.
- [107] Mohamed Abdelrahem, Christoph Michael Hackl, and Ralph Kennel. Implementation and experimental investigation of a sensorless field-oriented control scheme for permanent-magnet synchronous generators. *Electrical Engineering*, may 2017.

References XIII

- [108] A. D. Birda, J. Reuss, and C. Hackl. Synchronous optimal pulse-width modulation with differently modulated waveform symmetry properties for feeding synchronous motor with high magnetic anisotropy. In *2017 19th European Conference on Power Electronics and Applications (EPE'17 ECCE Europe)*, pages P.1–P.10, Sept 2017.
- [109] H. Eldeeb, C. Hackl, M. Abdelrahem, and A. S. Abdel-Khalik. A unified SVPWM realization for minimizing circulating currents of dual three phase machines. In *2017 IEEE 12th International Conference on Power Electronics and Drive Systems (PEDS)*, pages 925–931, Dec 2017.
- [110] Mauricio Espinoza, Matias Díaz, Enrique Espina, Christoph M. Hackl, and Roberto Cardénas. Control strategies for modular multilevel converters driving cage machines. In *Proceedings of the 3rd IEEE Southern Power Electronics Conference (SPEC 2017)*, pages 1–6, Dec 2017.
- [111] Mohamed Abdelrahem, Christoph M. Hackl, Zhenbin Zhang, and Ralph Kennel. Robust predictive control for direct-driven surface-mounted permanent-magnet synchronous generators without mechanical sensors. *IEEE Transactions on Energy Conversion*, 33(1):179–189, 2018.
- [112] Korbinian Schechner and Christoph M. Hackl. Scaling of the drive train dynamics of large-scale wind turbine systems for real-time emulation in small-scale laboratory setups. *IEEE Transactions on Industrial Electronics*, 66(9):6779–6788, 2018.
- [113] H. Eldeeb, A. S. Abdel-Khalik, and C. Hackl. Dynamic modelling of dual three-phase IPMSM drives with different neutral configurations. *IEEE Transactions on Industrial Electronics*, PP(99):1–1, 2018.
- [114] H. Eldeeb, M. Abdelrahem, C. Hackl, and A. S. Abdel-Khalik. Enhanced electromechanical modeling of asymmetrical dual three-phase IPMSM drives. In *2018 IEEE 27th International Symposium on Industrial Electronics (ISIE)*, pages 126–132, June 2018.
- [115] H. Eldeeb, A. S. Abdel-Khalik, and C. Hackl. Post-fault full torque-speed exploitation of dual three-phase IPMSM drives. *IEEE Transactions on Industrial Electronics*, 2018.
- [116] Hisham Magdy Eldeeb, Ayman Samy Abdel-Khalik, Julian Kullick, and Christoph M. Hackl. Pre and post-fault current control of dual three-phase reluctance synchronous drives. *IEEE Transactions on Industrial Electronics*, pages 1–1, 2019.

References XIV

- [117] Athina Birda, Jörg Reuss, and Christoph M. Hackl. Simple fundamental current estimation and smooth transition between synchronous optimal pwm and asynchronous svm. *IEEE Transactions on Industrial Electronics*, pages 1–1, 2019.
- [118] Xiaonan Gao, Mohamed Abdelrahem, Christoph M. Hackl, Zhenbin Zhang, and Ralph Kennel. Direct predictive speed control with a sliding manifold term for pmsm drives. *IEEE Journal of Emerging and Selected Topics in Power Electronics*, pages 1–1, 2019.
- [119] Mohamed Abdelrahem, Christoph Michael Hackl, Ralph Kennel, and José Rodríguez. Efficient direct-model predictive control with discrete-time integral action for pmsgs. *IEEE Transactions on Energy Conversion*, 34(2):1063–1072, 2019.
- [120] Mohamed Abdelrahem, Christoph Hackl, Ralph Kennel, and Jose Rodriguez. Sensorless predictive speed control of permanent-magnet synchronous generators in wind turbine applications. In *PCIM Europe 2019; International Exhibition and Conference for Power Electronics, Intelligent Motion, Renewable Energy and Energy Management*, pages 1–8, May 2019.
- [121] Shih-Wei Su, Ralph Kennel, and Christoph M. Hackl. Analytical flux linkage approximation prototypes for reluctance synchronous machines. In *2020 International Symposium on Power Electronics, Electrical Drives, Automation and Motion (SPEEDAM)*. IEEE, jun 2020.
- [122] Mohamed Abdelrahem, Christoph M. Hackl, José Rodríguez, and Ralph Kennel. Model reference adaptive system with finite-set for encoderless control of PMSGs in micro-grid systems. *Energies*, 13(18):4844, sep 2020.
- [123] Christoph Hackl, Julian Kullick, and Niklas Monzen. Optimale Betriebsführung für nichtlineare Synchronmaschinen. In Joachim Böcker and Gerd Griepentrog, editors, *Elektrische Antriebe – Regelung von Antriebssystemen*. Springer-Verlag, 2020.
- [124] Antonin Glac, Vaclav Smidl, Zdenek Peroutka, and Christoph M. Hackl. Comparison of IPMSM parameter estimation methods for motor efficiency. In *IECON 2020 The 46th Annual Conference of the IEEE Industrial Electronics Society*. IEEE, oct 2020.
- [125] Christoph Hackl, Julian Kullick, and Peter Landsmann. Nichtlineare Stromregelverfahren für Reluktanz-Synchronmaschinen. In Joachim Böcker and Gerd Griepentrog, editors, *Elektrische Antriebe – Regelung von Antriebssystemen*. Springer-Verlag, 2020.
- [126] Ahmed Farhan, Mohamed Abdelrahem, Christoph M. Hackl, Ralph Kennel, Adel Shaltout, and Amr Saleh. Advanced strategy of speed predictive control for nonlinear synchronous reluctance motors. *Machines*, 8(3):44, aug 2020.

References XV

- [127] Mohamed Abdelrahem, Christoph Hackl, Ralph Kennel, and Jose Rodriguez. Low sensitivity predictive control for doubly-fed induction generators based wind turbine applications. *Sustainability*, 13(16):9150.
- [128] Athina Birda, Joerg Reuss, and Christoph M. Hackl. Synchronous optimal pulsewidth modulation for synchronous machines with highly operating point dependent magnetic anisotropy. *IEEE Transactions on Industrial Electronics*, 68(5):3760–3769, may 2021.
- [129] Athina Birda, Christoph Grabher, Joerg Reuss, and Christoph M. Hackl. Dc-link capacitor and inverter current ripples in anisotropic synchronous motor drives produced by synchronous optimal pwm. *IEEE Transactions on Industrial Electronics*, jan 2021.
- [130] Andrea Zanelli, Julian Kullick, Hisham Eldeeb, Gianluca Frison, Christoph Hackl, and Moritz Diehl. Continuous control set nonlinear model predictive control of reluctance synchronous machines. *IEEE Transactions on Control Systems Technology*, pages 1–12, 2021.
- [131] C. M. Hackl, J. Kullick, and N. Monzen. Generic loss minimization for nonlinear synchronous machines by analytical computation of optimal reference currents considering copper and iron losses. In *2021 IEEE International Conference on Industrial Technology (ICIT)*. IEEE, mar 2021.
- [132] Mohamed Abdelrahem, Christoph M. Hackl, Ralph Kennel, and Jose Rodriguez. Computationally efficient finite-position-set-phase-locked loop for sensorless control of PMSGs in wind turbine applications. *IEEE Transactions on Power Electronics*, 36(3):3007–3016, mar 2021.
- [133] Antonín Glac, Václav Šmídl, Zdeněk Peroutka, and Christoph M. Hackl. Dependence of IPMSM motor efficiency on parameter estimates. *Sustainability*, 13(16):9299.
- [134] Haotian Xie, Jianming Du, Dongliang Ke, Yingjie He, Fengxiang Wang, Christoph Hackl, José Rodríguez, and Ralph Kennel. Multistep model predictive control for electrical drives—a fast quadratic programming solution. *Symmetry*, 14(3):626.
- [135] Issa Hammoud, Sebastian Hentzelt, Ke Xu, Thimo Oehlschlaegel, Mohamed Abdelrahem, Christoph M. Hackl, and Ralph Kennel. On continuous set model predictive control of permanent magnet synchronous machines. *IEEE Transactions on Power Electronics*, pages 1–1, 2022.

References XVI

- [136] Julian Kullick and Christoph M. Hackl. Speed-sensorless control of induction machines with LC filter for geothermal electric submersible pumping systems. *Machines*, 10(2):87.
- [137] Yuebin Pang, Jovan Knezevic, Daniel Glose, and Christoph Hackl. Sensorless control of electrically excited synchronous machines considering magnetic saturation and flux linkage dynamics for automotive applications. pages 1–11.
- [138] Simon Wiedemann and Christoph M. Hackl. Simultaneous identification of inverter and machine nonlinearities for self-commissioning of electrical synchronous machine drives. *IEEE Transactions on Energy Conversion*, pages 1–14, 2023.
- [139] Christian Dirscherl, Christoph Hackl, and Korbinian Schechner. Modellierung und Regelung von modernen Windkraftanlagen: Eine Einführung (see <https://arxiv.org/abs/1703.08661> for the english translation). In Dierk Schröder, editor, *Elektrische Antriebe – Regelung von Antriebssystemen*, chapter 24, pages 1540–1614. Springer-Verlag, 2015.
- [140] Florian Bauer, Christoph M. Hackl, and Korbinian Schechner. DC-link control for airborne wind energy systems during pumping mode. In *Proceedings of the Airborne Wind Energy Conference (AWEC 2015)*, Delft, Netherlands, 2015.
- [141] Mohamed Abdelrahem, Christoph M. Hackl, and Ralph Kennel. Model predictive control of permanent magnet synchronous generators in variable-speed wind turbine systems. In *Proceedings of the Power Electronics Student Summit (PESS 2016)*, Aachen, Germany, 2016.
- [142] Mohamed Abdelrahem, Christoph Michael Hackl, and Ralph Kennel. Simplified model predictive current control without mechanical sensors for variable-speed wind energy conversion systems. *Electrical Engineering*, 99(1):367–377, 2016.
- [143] Mohamed Abdelrahem, Christoph M. Hackl, Zhenbin Zhang, and Ralph Kennel. Sensorless control of permanent magnet synchronous generators in variable-speed wind turbine systems. In *Proceedings of the Power Electronics Student Summit (PESS 2016)*, Aachen, Germany, 2016.
- [144] Florian Bauer, Christoph M. Hackl, K. Smedley, and Ralph Kennel. Virtual-power-hardware-in-the-loop simulations in crosswind kite power with ground generation. In *Proceedings of the 2016 American Control Conference (ACC)*, pages 4071–4076, Boston, FL, USA, jul 2016. Institute of Electrical and Electronics Engineers (IEEE).

References XVII

- [145] Christian Dirscherl and Christoph M. Hackl. Dynamic power flow in wind turbine systems with doubly-fed induction generator. In *Proceedings of the 2016 IEEE International Energy Conference (ENERGYCON 2016)*, pages 1–6, Leuven, Belgium, apr 2016. Institute of Electrical and Electronics Engineers (IEEE).
- [146] Christoph M. Hackl and Korbinian Schechner. Non-ideal feedforward torque control of wind turbines: Impacts on annual energy production & gross earnings. In *Proceedings of the 6th edition of the conference “The Science of Making Torque from Wind” (TORQUE 2016)*, volume 753 of *Open access Journal of Physics: Conference Series 753 (2016) 112005*, page 112010, Munich, Germany, sep 2016. IOP Publishing.
- [147] Florian Bauer, Ralph M. Kennel, Christoph M. Hackl, Filippo Campagnolo, Michael Patt, and Roland Schmehl. Drag power kite with very high lift coefficient. *Renewable Energy*, October 2017.
- [148] Christian Dirscherl and Christoph M. Hackl. Local stability analysis and controller design for speed-controlled wind turbine systems in regime ii.5. *Energies*, (5):33, 2018.
- [149] Christoph M. Hackl, Pol Jané-Soneira, Martin Pfeifer, Korbinian Schechner, and Sören Hohmann. Full- and reduced-order state-space modeling of wind turbine systems with permanent magnet synchronous generator. *Energies*, (7):33, 2018.
- [150] S. Hanif, K. Zhang, C. Hackl, M. Barati, H. B. Gooi, and T. Hamacher. Decomposition and equilibrium achieving distribution locational marginal prices using trust-region method. *IEEE Transactions on Smart Grid*, PP(99):1–1, 2018.
- [151] Mohamed Abdelrahem, Christoph Hackl, Ahmed Farhan, and Ralph Kennel. Finite-set mras observer for encoderless control of pmsgs in wind turbine applications. In *2019 IEEE Conference on Power Electronics and Renewable Energy (CPERE)*, pages 431–436, 2019.
- [152] Katharina Bär, Abdessamad Saidi, Christoph Hackl, and Wilfried Zörner. Combined operation of photovoltaic and biogas plants for optimal transformer loading. *Chemical Engineering Transactions*, 76:601–606.
- [153] Kai Zhang, Sarmad Hanif, Christoph M. Hackl, and Thomas Hamacher. A framework for multi-regional real-time pricing in distribution grids. *IEEE Transactions on Smart Grid*, 10(6):6826–6838, Nov 2019.

References XVIII

- [154] Florian Bauer, Christoph M. Hackl, Keyue Smedley, and Ralph Kennel. Crosswind kite power with tower. In Roland Schmehl, editor, *Airborne Wind Energy: Advances in Technology Development and Research*. Springer-Verlag, 2019.
- [155] Florian Bauer, Christoph M. Hackl, Keyue Smedley, and Ralph Kennel. On multicopter-based launching and landing of lift power kites. In Roland Schmehl, editor, *Airborne Wind Energy: Advances in Technology Development and Research*. Springer-Verlag, 2019.
- [156] Mohamed Abdelrahem, Christoph Hackl, and Ralph Kennel. Robust predictive control scheme for permanent-magnet synchronous generators based modern wind turbines. *Electronics*, 10(13):1596.
- [157] D. Schröder and C.M. Hackl. Grundlagen der Regelungstechnik. IHK Schwaben, Mechatronik Weiterbildung, 2009.
- [158] Christoph Hackl. *Bewegungssteuerung durch geregelte elektrische Antriebe (Übung)*. Lehrstuhl für Elektrische Antriebe und Leistungselektronik – Technische Universität München, 2013.
- [159] Christoph M. Hackl. Regelung von regenerativen Energiesystemen (Vorlesungsskriptum und Übungsaufgaben). online, 2014. Lehrmaterialien zur Veranstaltung “Regelung von regenerativen Energiesystemen” im Wintersemester 2013/2014 an der Technischen Universität München.
- [160] Christoph M. Hackl. Projektstudium Antriebstechnik: Projektbezogen Studieren – Aktives Lernen im Team. online, 2015. Kurzschrift mit Projektbeschreibungen zur Umsetzung des Ernst-Otto Fischer Lehrpreises 2013 im Wintersemester 2014/2015 an der Technischen Universität München.
- [161] Christoph Hackl, Ellen Taraba, and Anne-Marie Fleischmann. Projektbezogen Studieren – Aktives Lernen im Team: Fachliche und überfachliche Kompetenzen von Studierenden fördern. In *Tagungsband des 2. HD-MINT-Symposium Hochschuldidaktik für MINT-Fächer*, Nürnberg, Germany, 2015.
- [162] Christoph M. Hackl, Anne-Marie Fleischmann, and Ellen Taraba. Projektstudium Antriebstechnik: Projektbezogen Studieren – Aktives Lernen im Team. In *Tagungsband des 5. VDI Qualitätsdialogs Lehre - Studienerfolg verbessern*, Tagungswerk Jerusalemkirche, Berlin, Germany, 2015.

References XIX

- [163] Christoph Hackl, Anne-Marie Lickert, and Ellen Taraba. Projektbezogen Studieren – Aktives Lernen im Team. In *Neues Handbuch Hochschullehre*, volume 76, pages 31–44. DUZ Medienhaus, 2016.
- [164] Shigeo Morimoto. Trend of permanent magnet synchronous machines. *IEEJ Transactions on Electrical and Electronic Engineering*, 2(2):101–108, mar 2007.
- [165] R.W.D Nickalls. The quartic equation: Invariants and Euler’s solution revealed. *Mathematical Gazette*, 93(526):66–75, mar 2009.
- [166] Antonin Glac, Vaclav Smidl, and Zdenek Peroutka. Optimal feedforward torque control of synchronous machines with time-varying parameters. In *Proceedings of the 44th Annual Conference of the IEEE Industrial Electronics Society (IECON)*. IEEE, oct 2018.
- [167] C. M. Hackl, J. Kullick, H. Eldeeb, and L. Horlbeck. Analytical computation of the optimal reference currents for MTPC/MTPA, MTPV and MTPF operation of anisotropic synchronous machines considering stator resistance and mutual inductance. In *2017 19th European Conference on Power Electronics and Applications (EPE’17 ECCE Europe)*, pages P.1–P.10, Sept 2017.
- [168] Dierk Schröder and Joachim Böcker, editors. *Elektrische Antriebe – Regelung von Antriebssystemen*. Springer Berlin Heidelberg, 2020.
- [169] M. Fakharmanesh, C. M. Hackl, and R. Perini. Instantaneous conduction and switching losses in two-level voltage source inverters. In *2017 IEEE International Conference on Environment and Electrical Engineering and 2017 IEEE Industrial and Commercial Power Systems Europe (EEEIC / I CPS Europe)*, pages 1–6, June 2017.